

Made in USA

dss

## **Duolok**® Tube Fittings



SSP

NOLOK

SSP SSP

iii







QUALITY INSTRUMENTATION FITTINGS



## **SSP Fittings Corp. / SSP Instrumentation**

### **Table of Contents**

| How to Order 3  |
|---|
| Tube Fittings<br>Selection Guide 4-6                      |
| Duolok Tube Fittings<br>General Information               |
| Interchangeability 8                                      |
| Installation Instructions 9                               |
| Presetting Tool 10  |
| Gageability 10  |
| Tube Fittings 11-47                                       |
| Components 48-49  |
| Selection Guide for Instrument<br>Fittings & Tubing 50-53 |
| Safety Information 54                                     |
| Warranty 54   |
|   |



### **SSP** Fittings Corp.

Since its inception in 1926, SSP has developed into an internationally recognized manufacturer of the highest quality, machined products. This successful U.S. corporation's heritage of craftsmanship and business expertise provide the foundation for an instrumentation division specializing in providing alternatives in instrumentation quality tube fittings.







NOTICE: This publication is an uncontrolled copy of a controlled document. SSP Instrumentation has made every reasonable effort to insure the accuracy of the information contained in this publication, and is not to be held liable in any manner for any mistakes, omissions, typographical and/or printing errors.

### **SSP Instrumentation**

It takes a team of experts working together to become a recognized leader in the instrumentation tube fitting marketplace. SSP Instrumentation combines the finest in manufacturing equipment and expertise with state-of-the-art design engineering, outstanding quality assurance, superior customer service, and an efficient inventory distribution system to accomplish the task.

Duolok® is a registered trademark of SSP Fittings Corp. Monel® is a registered trademark of Inco Alloys International Teflon® & Viton® are registered trademarks of E.I. duPont de Nemours Hastelloy® is a registered trademark of Haynes International Inc. Swagelok® is a registered trademark of the Swagelok Co. Tygon® is a registered trademark of Norton Performance Plastics Corp.

## How to Order Duolok Tube Fittings

### **Example: ISSD4MC2**



Tees and Crosses: Tees are described by first sizing the run (1 to 2) and then the branch (3). Crosses are described by first sizing the run (1 to 2) and then the branch (3 to 4). See Figure 1.



Specials: SSP Instrumentation manufactures a wide variety of special application tube fittings. Contact your local distributor for details regarding availability of special tube fitting configurations, materials and sizes.

| CHART #1            |                          |
|---------------------|--------------------------|
| Instrumentation     |                          |
| Material Designator | Material                 |
| IB                  | Brass                    |
| ISS                 | 316 Stainless Steel      |
| ICS                 | Carbon Steel             |
| ІНС                 | Hastelloy <sup>®</sup> C |
| IM                  | Monel®                   |
| IN*                 | Nylon                    |
| IPFA*               | PFA Teflon®              |
| ITFE*               | PTFE Teflon <sup>®</sup> |
| * Ferrules Only     |                          |

| CHART #2   | Part # Size Designators |
|------------|-------------------------|
| Size       | Tube O.D. or MNPT,      |
| Designator | FNPT Size*              |
| 1          | 1/16"                   |
| 2          | 1/8"                    |
| 3          | 3/16"                   |
| 4          | 1/4"                    |
| 5          | 5/16"                   |
| 6          | 3/8"                    |
| 8          | 1/2"                    |
| 10         | 5/8"                    |
| 12         | 3/4"                    |
| 16         | 1"                      |
| 20         | 1-1/4"                  |
| 24         | 1-1/2"                  |
| 32         | 2"                      |

\* Tube O.D. expressed in sixteenths of an inch

For special application tees, a 3rd end connection is required for a reduced size tube O.D. or a differing type of end connection such as MNPT, FNPT, etc. (See Chart#2)

| CHART #3     |   |
|--------------|---|
| Type of      | Description of Duolok                   |
| Tube Fitting | Tube Fitting Types                      |
| ANA          | AN Adapter                              |
| ANBU         | AN Bulkhead Union                       |
| ANF          | Female A/V Adapter                      |
| ANU          | A/V Union<br>Bulkhaad Famala Connector  |
| BFC          | Bulkhead Mala Connector                 |
|              | Bulkhead Reducer/Adapter                |
| BRII         | Bulkhead Reducing Union                 |
| BU           | Bulkhead Union                          |
| CP           | Сар                                     |
| CU           | Calibration Union                       |
| DA           | Dielectric Adapter                      |
| DU           | Dielectric Union                        |
| FA           | Female Adapter                          |
| FBT          | Female Branch Tee                       |
| FC           | Female Connector                        |
| FCRT         | Female Connector to ISO Tapered         |
| FE           | Female Elbow                            |
| FRT          | Female Run Tee                          |
| НВА          | Hose Barb Adapter                       |
| MAST         | Male Adapter to Straight Thread Boss    |
| MASI         | Male Branch Tee                         |
| MBTST        | Male Branch Tee to Straight Thread Boss |
| MC           | Male Connector                          |
| МСВТ         | Male Connector Bored Through            |
| MCRS         | Male Connector to ISO Parallel          |
| MCRT         | Male Connector to ISO Tapered           |
| MCST         | Male Connector to Straight Thread Boss  |
| ME           | Male Elbow                              |
| MERT         | Male Elbow to ISO Tapered               |
| MEST         | Male Elbow to Straight Thread Boss      |
| M45E         | Male 45° Elbow                          |
| M45EST       | Male Pipe Wold Connector                |
|              | Male Pipe Weld Elbow                    |
| MRT          | Male Run Tee                            |
| MRTST        | Male Run Tee to Straight Thread Boss    |
| OMC          | O-Ring Seal Male Pipe Connector         |
| OSC          | O-Ring Seal Straight Thread Connector   |
| Р            | Plug                                    |
| PC           | Port Connector                          |
| R            | Reducer/Adapter                         |
| RPC          | Reducing Port Connector                 |
| RU           | Reducing Union                          |
| TSWE         | Tube Socket Weld Lipion                 |
| 1500         |   |
|              | Union Cross                             |
| UE           | Union Elbow                             |
| UT           | Union Tee                               |
|              | COMPONENTS                              |
| BF           | Back Ferrule                            |
| BN           | Bulkhead Nut                            |
| FF           | Front Ferrule                           |
| FS           | Ferrule Set                             |
| KN           | Knurled Nut                             |
| N            | Nut                                     |
| n I          | I I UDE INSERT                          |

## **Duolok Tube Fittings Selection Guide**



**Tube to Female Pipe Bulkhead Female** Female Connector Connector FC BFC 19 20 Female Elbow Female Adapter FE FA 35 22 Female Branch Tee Female Run Tee 山田田 FRT **FBT** 23 21

Our selection guide makes it easy to locate any fitting. Simply turn to the page designated in the lower right hand corner.

## **Duolok Tube Fittings Selection Guide**







## **Duolok Tube Fittings Selection Guide**

### **Duolok to 37° Flare (***AN***)**



### Tube to O-Ring Seal & Tube to SAE / MS





### Components

| Nut         | Back Ferrule     | Front Ferrule | Ferrule Set        |
|-------------|------------------|---------------|--------------------|
| gss<br>Ssp  | 0                |               | kaladadadadadadada |
| N 48        | BF 48            | FF 48         | FS 48              |
| Knurled Nut | Bulkhead Locknut | Tube Insert   |                    |
| SSP         |                  |               |                    |
| KN 49       | BN 49            | TI 49         |                    |

## **Duolok Tube Fittings**

### DESIGN

**Duolok** tube fittings are designed and manufactured to provide a reliable, leak-proof connection in instrumentation and process tubing systems. **Duolok** tube fittings consist of four precision-machined components:

- 1) Body
  - 2) Front Ferrule
  - 3) Back Ferrule
    - 4) Nut



The double ferrule design, with the staged sequential swaging action of the ferrules during make-up, compensates for the variations in tubing materials, hardness, and thickness of the tube wall to provide leak-tight connections in an extensive range of applications.

Additionally, in fulfillment of the design criteria, all **Duolok** components are manufactured with stringent tolerances and superior surface finishes under rigorous quality control standards to assure the optimum performance of each component.

### **OPERATION**

Through the critical interaction of precision-machined fitting components with the process tube, a leak-tight seal is achieved.

The simple geometric rotation of the **Duolok** nut provides the axial thrust necessary to swage the ferrules to the outside diameter of the tube. To eliminate any potential stress on an existing system, the tube fittings have been designed to not transmit installation torque from the tube fittings to the tubing.

During the rotary movement of the nut, the internal surface of the nut meets with the rear surface of the back ferrule to axially move the back ferrule forward against the rear angle of the front ferrule.

Simultaneously, the front ferrule is driven forward into the angular section of the fitting body where the desired "lift to seal" action of the front ferrule occurs. The back ferrule "locks" on the outside diameter of the tube to complete the sealing action and secure the tube within the fitting.

The resulting "engineered gap" between the front and back ferrule is designed to help compensate for exposure to system variables such as vibration, pressure pulsation and thermal expansion/contraction.

### QUALITY

SSP's Quality System has been certified to conform to the **ISO 9001:2000 Quality Standard**. Achievement of this prestigious status further confirms SSP's continuing commitment to quality which is reflected throughout the company in its personnel, policies, equipment, products and service.

In addition, all **Duolok** tube fittings are manufactured to the technical design specifications and



rigid quality control standards of the SSP Instrumentation Division.

### **Statistical Process Control**

techniques are employed within the manufacturing process to supply timely, meaningful feedback to the production team. Continual process monitoring and equipment control provide the necessary manufacturing quality for **Duolok** instrumentation grade tube fittings.

### PACKAGING

**Duolok** tube fittings are individually bagged to assure the highest levels of quality, safety and cleanliness. The protective bags eliminate contamination (tubing burrs, dirt, etc.) from entering the fitting prior to its use, and help to retain the integrity of the factory assembled body, nut, and ferrules.



As long as a **Duolok** tube fitting is in its original protective bag, it is identified as factory new, completely assembled and ready for installation.

Additionally, for efficient product identification and storage, the **Duolok** tube fittings are packaged in boxes that are color-coded to the tube fittings' material of construction and have pictorial labels which include the part number, product description and box quantity.

## **Duolok Tube Fittings**

### MATERIALS

### **316 STAINLESS STEEL**

**Duolok** straight configuration tube fittings are machined from type 316 stainless steel cold-finished bar stock in accordance with ASTM A-276 and ASTM A-479. Shaped bodies are machined from close-grained 316 stainless steel forgings in accordance with ASTM A-182. All 316 stainless steel **Duolok** components are heat code traceable with certified material test reports (CMTRs) available.

### BRASS

**Duolok** straight configuration tube fittings are machined from CA360 and CA345 premium brass bar stock in accordance with ASTM B-16 and ASTM B-453. Shaped bodies are machined from precision forgings of CA-377 brass in accordance with ASTM B-124.

### PRESSURE RATINGS

Generally, **Duolok** tube fittings are rated for pressures equal to the maximum allowable working pressures of the tubing recommended for use with the fittings. However, it is important to note that many specially designed fittings, bored-through fittings and fittings having AN, O-Seal and SAE/MS integral ends may have lower pressure ratings than that of the tubing. (See SSP's Selection Guide for Instrumentation Fittings and Tubing on pages 50-53 or contact your local Authorized Distributor for more information regarding tubing and fitting pressure ratings.)

### **TEMPERATURE FACTORS**

**Duolok** tube fittings function reliably in applications ranging from cryogenic temperatures to high temperature bake out with the tube fitting material as the limiting factor. It is important to note that elevated temperatures will reduce the maximum working pressure capability of the tubing system. (For more information regarding the effects of temperature on tubing pressure ratings, refer to Table 5 regarding temperature stress factors in SSP's Selection Guide for Instrumentation Fittings and Tubing on pages 50-53).

### GAGEABILITY

**Duolok** tube fittings are designed, manufactured and quality controlled to be *gageable* for sufficient pull-up during initial installation. See page 10 for additional information.

### **INTERCHANGEABILITY**

Duolok tube fittings are designed, manufactured and quality controlled to be totally "interchangeable" with the Swagelok® brand of tube fittings. Component by component examination by SSP Fittings plainly shows the two brands as completely "componentintermixable." The precision manufacturing of both products to stringent tolerances under rigid quality control procedures ensures the safety, performance and reliability of service whenever Duolok and Swagelok component parts are mixed and used in accordance with published installation and service recommendations of SSP Fittings.

### LIFETIME WARRANTY

**Duolok** tube fittings are covered by a published Lifetime Warranty as printed on page 54.

### **TUBE SELECTION**

Careful selection and specification of tubing is essential to the performance of a tubing system. When choosing the appropriate tubing material, size and wall thickness, consideration must be given to the system's environment, pressures, temperatures and flows. (For more information on tube selection, please refer to SSP's *Selection Guide for Instrumentation Fittings and Tubing* on pages 50-53.)



Duolok

Swagelok

## **Duolok Installation Instructions**

### INITIAL INSTALLATION

1. Duolok tube fittings come individually bagged and completely assembled for immediate use. There is no need for disassembly prior to use. Simply remove the tube fitting from its bag, insert the tube\* until it bottoms in the **Duolok** tube fitting body and then hand tighten the **Duolok** nut. (See Figure #1.)

\*Tubing ends should be cut as straight as possible with all O.D. and I.D. burrs removed. Use of a tubing cutter or guide blocks with a hacksaw is recommended.



Note: For extreme system applications using high pressures or requiring an extra factor of safety, it may be desirable to use a "common makeup starting point" to alleviate the inherent variations in tubing diameters. Installation should begin from a "snug" position, which is achieved by wrench tightening the Duolok nut until the inserted tubing will not move freely by hand (approximately 1/8 turn). From this new "snug" starting point, continue with the recommended installation instructions.

2. While holding the fitting body stable with a back-up wrench, scribe the nut for a reference point and wrench tighten the nut 1-1/4 turns for sizes 1/4" - 1" and 3/4 turn for sizes 1/16"-3/16". (See Figures #2 and #3.)





Note: For all sizes, tighten plugs (P), machined ferrule end of port connector (PC) and the **Duolok** end of the Female AN adapter (ANF) only **1/4** of a turn. Tube fittings in sizes over 1" require the use of the SSP Instrumentation Hydraulic Swaging Tool for installation. Contact your Authorized SSP Instrumentation Distributor for more information.

### REASSEMBLY INSTRUCTIONS

1. To reassemble a **Duolok** tube fitting connection, simply insert the tubing with the previously swaged ferrules and **Duolok** nut into the fitting body until the front ferrule seats within the fitting body, and then tighten the nut by hand. (See Figure #4.)



*Note:* By following proper reassembly procedures, *Duolok* tube fitting connections may be disconnected and reconnected repeatedly.

2. While holding the fitting body stable with a back-up wrench, use a wrench to rotate the **Duolok** nut to the fitting's original installation position (approximately 1/4 turn from the hand-tight, snug position) then continue to tighten the **Duolok** nut slightly. (See Figure #5.)



### **COMPONENT ASSEMBLY**

Should individual component assembly of a **Duolok** tube fitting ever be required, careful attention must be given to the proper sequence and direction of the **Duolok** components. (See Figure #6.)



## **Pre-setting Tool/Gap Gage**

The **Duolok** pre-setting tool is used to pre-set the ferrules on the tubing for subsequent installation in a fitting body. The pre-setting tool can be especially helpful when an installation must be made in a tight space or hard-to-work area. The presetting tool allows the major portion of the installation work to occur in a more favorable work setting with only the completion of the installation in the hard-to-work area.

### PRE-SETTING INSTRUCTIONS

**1.** Secure the pre-setting tool in a vise.

2. Remove the protective nut, and assemble the **Duolok** nut and ferrules loosely to the pre-setting tool. Insert the tubing through the nut and ferrules until it bottoms in the pre-setting tool, and then follow the standard **Duolok** tube fitting installation instructions from page 9. (See Figure #7A and #7B)



**3.** Loosen the nut and remove the tubing with the pre-set **Duolok** ferrules and nut from the presetting tool. (See Figure #8.) Return the protective nut to the presetting tool.



4. Installation of the tubing, with the pre-set **Duolok** ferrules and nut in the appropriate fitting body, can now be made by following the standard reassembly instructions from page 9. (See Figure #9A and #9B.)



Note: To extend the life of a pre-setting tool, lubricate the tool with a lubricant compatible with the system's tubing material, environment and media. Also, at times an oversized or very soft tubing may tend to stick in the presetting tool after make up. To remove the tubing, gently rock the tube back and forth. Never turn the tube with pliers or another tool as such action may damage the sealing surfaces.

### GAGEABILITY

Each Duolok tube fitting component is manufactured with utmost precision to provide the optimum performance interaction of the components during assembly. By maintaining such stringent manufacturing tolerances, **Duolok** tube fittings are considered gageable for sufficient pull-up during initial installation. The **Duolok** "Gap Gages" are designed to identify for the installer or inspector, prior to pressurizing a system, that sufficient tightening of the tube fitting has occurred. Gageability provides additional reliability for proper installation and ultimate tube fitting safety and performance.

### DUOLOK GAP GAGE INSTRUCTIONS

**1.** Follow proper installation instructions (as supplied with the fittings, or published in the **Duolok** catalog).

2. After completion of the installation instructions and prior to pressuring the system, choose the proper size Gap Gage and try to insert it between the fitting's nut and body hex. (See Figure #10.)

**3.** If the Gap Gage will not enter between the fitting's nut and body hex, no additional tightening is required.

**4.** If the Gap Gage will enter between the fitting's nut and body hex, additional tightening is required.

**Note:** Swagelok Gap Inspection Gages may also be utilized effectively with Duolok tube fittings.



### ORDERING INFORMATON

To order Duolok presetting tools and gap gages, contact your authorized SSP Instrumentation distributor.





### Male Connector

|         | Т     | P-NPT     |      |      |      |      | Е       |      |       |        |
|---------|-------|-----------|------|------|------|------|---------|------|-------|--------|
| Duolok  | Tube  | Male Pipe |      |      |      |      | Minimum | F    |       |        |
| Part #  | O.D.  | Size      | A    | в    | с    | D    | Opening | Min. | G     | н      |
| D1MC1   | 1/16  | 1/16      | 0.94 | 0.79 | 0.43 | 0.34 | 0.05    | 0.38 | 5/16  | 5/16   |
| D1MC2   | 1/16  | 1/8       | 1.03 | 0.88 | 0.43 | 0.34 | 0.05    | 0.38 | 5/16  | 7/16   |
| D1MC4   | 1/16  | 1/4       | 1.22 | 1.07 | 0.43 | 0.34 | 0.05    | 0.56 | 5/16  | 9/16   |
| D2MC1   | 1/8   | 1/16      | 1.17 | 0.91 | 0.60 | 0.50 | 0.09    | 0.38 | 7/16  | 7/16   |
| D2MC2   | 1/8   | 1/8       | 1.20 | 0.94 | 0.60 | 0.50 | 0.09    | 0.38 | 7/16  | 7/16   |
| D2MC4   | 1/8   | 1/4       | 1.40 | 1.14 | 0.60 | 0.50 | 0.09    | 0.56 | 7/16  | 9/16   |
| D2MC6   | 1/8   | 3/8       | 1.41 | 1.15 | 0.60 | 0.50 | 0.09    | 0.56 | 7/16  | 11/16  |
| D2MC8   | 1/8   | 1/2       | 1.66 | 1.40 | 0.60 | 0.50 | 0.09    | 0.75 | 7/16  | 7/8    |
| D3MC2   | 3/16  | 1/8       | 1.23 | 0.97 | 0.63 | 0.54 | 0.12    | 0.38 | 1/2   | 7/16   |
| D3MC4   | 3/16  | 1/4       | 1.43 | 1.17 | 0.63 | 0.54 | 0.12    | 0.56 | 1/2   | 9/16   |
| D4MC1   | 1/4   | 1/16      | 1.29 | 1.00 | 0.70 | 0.60 | 0.11    | 0.38 | 9/16  | 1/2    |
| D4MC2   | 1/4   | 1/8       | 1.29 | 1.00 | 0.70 | 0.60 | 0.17    | 0.38 | 9/16  | 1/2    |
| D4MC4   | 1/4   | 1/4       | 1.49 | 1.20 | 0.70 | 0.60 | 0.19    | 0.56 | 9/16  | 9/16   |
| D4MC6   | 1/4   | 3/8       | 1.51 | 1.22 | 0.70 | 0.60 | 0.19    | 0.56 | 9/16  | 11/16  |
| D4MC8   | 1/4   | 1/2       | 1.76 | 1.47 | 0.70 | 0.60 | 0.19    | 0.75 | 9/16  | 7/8    |
| D4MC12  | 1/4   | 3/4       | 1.82 | 1.53 | 0.70 | 0.60 | 0.19    | 0.75 | 9/16  | 1-1/16 |
| D5MC2   | 5/16  | 1/8       | 1.34 | 1.05 | 0.73 | 0.64 | 0.19    | 0.38 | 5/8   | 9/16   |
| D5MC4   | 5/16  | 1/4       | 1.52 | 1.23 | 0.73 | 0.64 | 0.25    | 0.56 | 5/8   | 9/16   |
| D5MC6   | 5/16  | 3/8       | 1.54 | 1.25 | 0.73 | 0.64 | 0.25    | 0.56 | 5/8   | 11/16  |
| D6MC2   | 3/8   | 1/8       | 1.39 | 1.10 | 0.76 | 0.66 | 0.19    | 0.38 | 11/16 | 5/8    |
| D6MC4   | 3/8   | 1/4       | 1.57 | 1.28 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 5/8    |
| D6MC6   | 3/8   | 3/8       | 1.57 | 1.28 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 11/16  |
| D6MC8   | 3/8   | 1/2       | 1.82 | 1.53 | 0.76 | 0.66 | 0.28    | 0.75 | 11/16 | 7/8    |
| D6MC12  | 3/8   | 3/4       | 1.88 | 1.59 | 0.76 | 0.66 | 0.28    | 0.75 | 11/16 | 1-1/16 |
| D8MC2   | 1/2   | 1/8       | 1.53 | 1.13 | 0.86 | 0.90 | 0.19    | 0.38 | 7/8   | 13/16  |
| D8MC4   | 1/2   | 1/4       | 1.71 | 1.31 | 0.86 | 0.90 | 0.28    | 0.56 | 7/8   | 13/16  |
| D8MC6   | 1/2   | 3/8       | 1.71 | 1.31 | 0.86 | 0.90 | 0.38    | 0.56 | 7/8   | 13/16  |
| D8MC8   | 1/2   | 1/2       | 1.93 | 1.53 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 7/8    |
| D8MC12  | 1/2   | 3/4       | 1.99 | 1.59 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 1-1/16 |
| D8MC16  | 1/2   | 1         | 2.25 | 1.85 | 0.86 | 0.90 | 0.41    | 0.94 | 7/8   | 1-3/8  |
| D10MC6  | 5/8   | 3/8       | 1.74 | 1.34 | 0.86 | 0.96 | 0.38    | 0.56 | 1     | 15/16  |
| D10MC8  | 5/8   | 1/2       | 1.93 | 1.53 | 0.86 | 0.96 | 0.47    | 0.75 | 1     | 15/16  |
| D10MC12 | 5/8   | 3/4       | 1.99 | 1.59 | 0.86 | 0.96 | 0.50    | 0.75 | 1     | 1-1/16 |
| D12MC8  | 3/4   | 1/2       | 1.99 | 1.59 | 0.86 | 0.96 | 0.47    | 0.75 | 1-1/8 | 1-1/16 |
| D12MC12 | 3/4   | 3/4       | 1.99 | 1.59 | 0.86 | 0.96 | 0.62    | 0.75 | 1-1/8 | 1-1/16 |
| D12MC16 | 3/4   | 1         | 2.25 | 1.85 | 0.86 | 0.96 | 0.62    | 0.94 | 1-1/8 | 1-3/8  |
| D14MC12 | 7/8   | 3/4       | 1.99 | 1.59 | 0.86 | 1.02 | 0.62    | 0.75 | 1-1/4 | 1-3/16 |
| D14MC16 | 7/8   | 1         | 2.25 | 1.85 | 0.86 | 1.02 | 0.72    | 0.94 | 1-1/4 | 1-3/8  |
| D16MC8  | 1     | 1/2       | 2.26 | 1.78 | 1.04 | 1.23 | 0.47    | 0.75 | 1-1/2 | 1-3/8  |
| D16MC12 | 1     | 3/4       | 2.26 | 1.78 | 1.04 | 1.23 | 0.62    | 0.75 | 1-1/2 | 1-3/8  |
| D16MC16 | 1     | 1         | 2.45 | 1.97 | 1.04 | 1.23 | 0.88    | 0.94 | 1-1/2 | 1-3/8  |
| D20MC16 | 1-1/4 | 1         | 3.04 | 2.17 | 1.53 | 1.62 | 0.88    | 0.94 | 1-7/8 | 1-3/4  |
| D20MC20 | 1-1/4 | 1-1/4     | 3.04 | 2.17 | 1.53 | 1.62 | 1.09    | 0.94 | 1-7/8 | 1-3/4  |
| D24MC24 | 1-1/2 | 1-1/2     | 3.50 | 2.43 | 1.78 | 1.97 | 1.34    | 1.03 | 2-1/4 | 2-1/8  |
| D32MC32 | 2     | 2         | 4.47 | 3.00 | 2.47 | 2.66 | 1.81    | 1.06 | 3     | 2-3/4  |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.





### Male Connector - ISO Parallel

|           | Т    | Р         |      |      |      |      |      | н      |      |       |      |
|-----------|------|-----------|------|------|------|------|------|--------|------|-------|------|
| Duolok    | Tube | ISO       |      |      |      |      |      | Hex    |      |       | В    |
| Part #    | O.D. | Male Pipe | A    | F    | С    | D    | E    | Flat   | Ну   | G     | Body |
| D2MCRS2   | 1/8  | 1/8       | 1.18 | 0.28 | 0.60 | 0.50 | 0.09 | 9/16   | 0.54 | 7/16  | 0.92 |
| D2MCRS4   | 1/8  | 1/4       | 1.39 | 0.44 | 0.60 | 0.50 | 0.09 | 3/4    | 0.71 | 7/16  | 1.13 |
| D2MCRS6   | 1/8  | 3/8       | 1.43 | 0.44 | 0.60 | 0.50 | 0.09 | 7/8    | 0.86 | 7/16  | 1.17 |
| D4MCRS2   | 1/4  | 1/8       | 1.27 | 0.28 | 0.70 | 0.60 | 0.16 | 9/16   | 0.54 | 9/16  | 0.98 |
| D4MCRS4   | 1/4  | 1/4       | 1.48 | 0.44 | 0.70 | 0.60 | 0.19 | 3/4    | 0.71 | 9/16  | 1.19 |
| D4MCRS6   | 1/4  | 3/8       | 1.53 | 0.44 | 0.70 | 0.60 | 0.19 | 7/8    | 0.86 | 9/16  | 1.24 |
| D4MCRS8   | 1/4  | 1/2       | 1.76 | 0.56 | 0.70 | 0.60 | 0.19 | 1-1/16 | 1.02 | 9/16  | 1.47 |
| D6MCRS4   | 3/8  | 1/4       | 1.54 | 0.44 | 0.76 | 0.66 | 0.23 | 3/4    | 0.71 | 11/16 | 1.25 |
| D6MCRS6   | 3/8  | 3/8       | 1.59 | 0.44 | 0.76 | 0.66 | 0.28 | 7/8    | 0.86 | 11/16 | 1.30 |
| D6MCRS8   | 3/8  | 1/2       | 1.82 | 0.56 | 0.76 | 0.66 | 0.28 | 1-1/16 | 1.02 | 11/16 | 1.53 |
| D8MCRS4   | 1/2  | 1/4       | 1.68 | 0.44 | 0.86 | 0.90 | 0.23 | 13/16  | 0.71 | 7/8   | 1.28 |
| D8MCRS6   | 1/2  | 3/8       | 1.70 | 0.44 | 0.86 | 0.90 | 0.31 | 7/8    | 0.86 | 7/8   | 1.30 |
| D8MCRS8   | 1/2  | 1/2       | 1.93 | 0.56 | 0.86 | 0.90 | 0.41 | 1-1/16 | 1.02 | 7/8   | 1.53 |
| D12MCRS8  | 3/4  | 1/2       | 1.93 | 0.56 | 0.86 | 0.96 | 0.47 | 1-1/16 | 1.02 | 1-1/8 | 1.53 |
| D12MCRS12 | 3/4  | 3/4       | 2.08 | 0.62 | 0.86 | 0.96 | 0.62 | 1-5/16 | 1.26 | 1-1/8 | 1.68 |
| D16MCRS8  | 1    | 1/2       | 2.20 | 0.56 | 1.04 | 1.23 | 0.47 | 1-3/8  | 1.02 | 1-1/2 | 1.72 |
| D16MCRS16 | 1    | 1         | 2.36 | 0.72 | 1.04 | 1.23 | 0.78 | 1-5/8  | 1.54 | 1-1/2 | 1.88 |

NOTE: RS threaded fittings conform to ISO (International Standards Organization) standards 228/1. The standard gasket for RS fittings is a composite gasket. This gasket features a 300 series stainless steel outer ring with a Buna inner ring bonded to it.

> Duolok tube fittings are designed and manufactured to provide safe, reliable leak free tubing connections.





### Male Connector - ISO Tapered

|           |      | Р    |      |      |      |      |         |        |       |      |
|-----------|------|------|------|------|------|------|---------|--------|-------|------|
|           | т    | ISO  |      |      |      |      | E       | н      | G     |      |
| Duolok    | Tube | Male |      |      |      |      | Min.    | Hex    | Hex   | В    |
| Part #    | O.D. | Pipe | Α    | F    | С    | D    | Opening | Flat   | Flat  | Body |
| D2MCRT2   | 1/8  | 1/8  | 1.20 | 0.38 | 0.60 | 0.50 | 0.09    | 7/16   | 7/16  | 0.94 |
| D2MCRT4   | 1/8  | 1/4  | 1.40 | 0.56 | 0.60 | 0.50 | 0.09    | 9/16   | 7/16  | 1.14 |
| D4MCRT2   | 1/4  | 1/8  | 1.29 | 0.38 | 0.70 | 0.60 | 0.19    | 1/2    | 9/16  | 1.00 |
| D4MCRT4   | 1/4  | 1/4  | 1.49 | 0.56 | 0.70 | 0.60 | 0.19    | 9/16   | 9/16  | 1.20 |
| D4MCRT6   | 1/4  | 3/8  | 1.51 | 0.56 | 0.70 | 0.60 | 0.19    | 11/16  | 9/16  | 1.22 |
| D4MCRT8   | 1/4  | 1/2  | 1.76 | 0.75 | 0.70 | 0.60 | 0.19    | 7/8    | 9/16  | 1.47 |
| D5MCRT2   | 5/16 | 1/8  | 1.34 | 0.38 | 0.73 | 0.64 | 0.19    | 9/16   | 5/8   | 1.05 |
| D5MCRT4   | 5/16 | 1/4  | 1.52 | 0.56 | 0.73 | 0.64 | 0.25    | 9/16   | 5/8   | 1.23 |
| D6MCRT2   | 3/8  | 1/8  | 1.39 | 0.38 | 0.76 | 0.66 | 0.19    | 5/8    | 11/16 | 1.10 |
| D6MCRT4   | 3/8  | 1/4  | 1.57 | 0.56 | 0.76 | 0.66 | 0.28    | 5/8    | 11/16 | 1.28 |
| D6MCRT6   | 3/8  | 3/8  | 1.57 | 0.56 | 0.76 | 0.66 | 0.28    | 11/16  | 11/16 | 1.28 |
| D6MCRT8   | 3/8  | 1/2  | 1.82 | 0.75 | 0.76 | 0.66 | 0.28    | 7/8    | 11/16 | 1.53 |
| D8MCRT4   | 1/2  | 1/4  | 1.71 | 0.56 | 0.86 | 0.90 | 0.28    | 13/16  | 7/8   | 1.31 |
| D8MCRT6   | 1/2  | 3/8  | 1.71 | 0.56 | 0.86 | 0.90 | 0.38    | 13/16  | 7/8   | 1.31 |
| D8MCRT8   | 1/2  | 1/2  | 1.93 | 0.75 | 0.86 | 0.90 | 0.41    | 7/8    | 7/8   | 1.53 |
| D8MCRT12  | 1/2  | 3/4  | 1.99 | 0.75 | 0.86 | 0.90 | 0.41    | 1-1/16 | 7/8   | 1.59 |
| D12MCRT12 | 3/4  | 3/4  | 1.99 | 0.75 | 0.86 | 0.96 | 0.62    | 1-1/16 | 1-1/8 | 1.59 |
| D16MCRT16 | 1    | 1    | 245  | 0.94 | 1 04 | 1 23 | 0.88    | 1-3/8  | 1-1/2 | 1 97 |

NOTE: RT threaded fittings conform to ISO (International Standards Organization) standards 7/1.





### Male Connector - Bored Through

|           | Т     | P-NPT     |      |      |      |      |       |        |
|-----------|-------|-----------|------|------|------|------|-------|--------|
| Duolok    | Tube  | Male Pipe |      |      |      | F    |       |        |
| Part #    | O.D.  | Size      | Α    | В    | С    | Min. | G     | н      |
| D1MCBT1   | 1/16  | 1/16      | 0.94 | 0.79 | 0.43 | 0.38 | 5/16  | 5/16   |
| D1MCBT2   | 1/16  | 1/8       | 1.03 | 0.88 | 0.43 | 0.38 | 5/16  | 7/16   |
| D2MCBT1   | 1/8   | 1/16      | 1.17 | 0.91 | 0.60 | 0.38 | 7/16  | 7/16   |
| D2MCBT2   | 1/8   | 1/8       | 1.20 | 0.94 | 0.60 | 0.38 | 7/16  | 7/16   |
| D2MCBT4   | 1/8   | 1/4       | 1.40 | 1.14 | 0.60 | 0.56 | 7/16  | 9/16   |
| D3MCBT2   | 3/16  | 1/8       | 1.23 | 0.97 | 0.63 | 0.38 | 1/2   | 7/16   |
| D3MCBT4   | 3/16  | 1/4       | 1.43 | 1.17 | 0.63 | 0.56 | 1/2   | 9/16   |
| D4MCBT2   | 1/4   | 1/8       | 1.29 | 1.00 | 0.70 | 0.38 | 9/16  | 1/2    |
| D4MCBT4   | 1/4   | 1/4       | 1.49 | 1.20 | 0.70 | 0.56 | 9/16  | 9/16   |
| D4MCBT6   | 1/4   | 3/8       | 1.51 | 1.22 | 0.70 | 0.56 | 9/16  | 11/16  |
| D4MCBT8   | 1/4   | 1/2       | 1.76 | 1.47 | 0.70 | 0.75 | 9/16  | 7/8    |
| D5MCBT4   | 5/16  | 1/4       | 1.52 | 1.23 | 0.73 | 0.56 | 5/8   | 9/16   |
| D6MCBT4   | 3/8   | 1/4       | 1.57 | 1.28 | 0.76 | 0.56 | 11/16 | 5/8    |
| D6MCBT6   | 3/8   | 3/8       | 1.57 | 1.28 | 0.76 | 0.56 | 11/16 | 11/16  |
| D6MCBT8   | 3/8   | 1/2       | 1.82 | 1.53 | 0.76 | 0.75 | 11/16 | 7/8    |
| D8MCBT8   | 1/2   | 1/2       | 1.93 | 1.53 | 0.86 | 0.75 | 7/8   | 7/8    |
| D10MCBT12 | 5/8   | 3/4       | 1.99 | 1.59 | 0.86 | 0.75 | 1     | 1-1/16 |
| D12MCBT12 | 3/4   | 3/4       | 1.99 | 1.59 | 0.86 | 0.75 | 1-1/8 | 1-1/16 |
| D16MCBT16 | 1     | 1         | 2.45 | 1.97 | 1.04 | 0.94 | 1-1/2 | 1-3/8  |
| D20MCBT20 | 1-1/4 | 1-1/4     | 3.04 | 2.17 | 1.53 | 0.94 | 1-7/8 | 1-3/4  |

### **Thermocouple Connector**

To accommodate thermocouples and other sensing probes, the MCBT series of fittings has been "bored through" to allow the thermocouple or sensor to extend beyond the end of the fitting's NPT thread.

**Note:** Pressure Ratings of "bored through" tube fittings are reduced. For additional information on a specific fitting's rating, contact the local distributor.







### Bulkhead Male Connector

|        | Т    | P-NPT     |      |      |      |      |      | Е       |      |       |       |       | Maximum   | Panel      |
|--------|------|-----------|------|------|------|------|------|---------|------|-------|-------|-------|-----------|------------|
| Duolok | Tube | Male Pipe |      |      |      |      |      | Minimum | F    |       |       |       | Panel     | Hole Drill |
| Part # | O.D. | Size      | Α    | Ax   | В    | Bx   | D    | Opening | Min. | G     | н     | Нx    | Thickness | Size       |
| D2BMC2 | 1/8  | 1/8       | 1.83 | 1.23 | 1.57 | 0.97 | 0.50 | 0.09    | 0.38 | 7/16  | 1/2   | 1/2   | 0.50      | 21/64      |
| D4BMC2 | 1/4  | 1/8       | 1.95 | 1.32 | 1.66 | 1.03 | 0.60 | 0.17    | 0.38 | 9/16  | 5/8   | 5/8   | 0.40      | 29/64      |
| D4BMC4 | 1/4  | 1/4       | 2.10 | 1.32 | 1.81 | 1.03 | 0.60 | 0.19    | 0.56 | 9/16  | 5/8   | 5/8   | 0.40      | 29/64      |
| D6BMC4 | 3/8  | 1/4       | 2.26 | 1.45 | 1.97 | 1.16 | 0.66 | 0.28    | 0.56 | 11/16 | 3/4   | 3/4   | 0.44      | 37/64      |
| D8BMC6 | 1/2  | 3/8       | 2.49 | 1.65 | 2.09 | 1.25 | 0.90 | 0.37    | 0.56 | 7/8   | 15/16 | 15/16 | 0.50      | 49/64      |
| D8BMC8 | 1/2  | 1/2       | 2.71 | 1.65 | 2.31 | 1.25 | 0.90 | 0.41    | 0.75 | 7/8   | 15/16 | 15/16 | 0.50      | 49/64      |





### 45° Male Elbow

|         | Т    | P-NPT     |      |      |      |      |      | E       |      |       |       |
|---------|------|-----------|------|------|------|------|------|---------|------|-------|-------|
| Duolok  | Tube | Male Pipe |      |      |      |      |      | Minimum | F    |       |       |
| Part #  | O.D. | Size      | Α    | Вx   | Ву   | С    | D    | Opening | Min. | G     | н     |
| D4M45E2 | 1/4  | 1/8       | 0.97 | 0.68 | 0.65 | 0.70 | 0.60 | 0.17    | 0.38 | 9/16  | 9/16  |
| D4M45E4 | 1/4  | 1/4       | 0.97 | 0.68 | 0.83 | 0.70 | 0.60 | 0.19    | 0.56 | 9/16  | 9/16  |
| D6M45E2 | 3/8  | 1/8       | 1.10 | 0.81 | 0.72 | 0.76 | 0.66 | 0.19    | 0.38 | 11/16 | 5/8   |
| D6M45E4 | 3/8  | 1/4       | 1.10 | 0.81 | 0.90 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 5/8   |
| D6M45E6 | 3/8  | 3/8       | 1.15 | 0.86 | 0.95 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 3/4   |
| D8M45E6 | 1/2  | 3/8       | 1.26 | 0.86 | 0.95 | 0.86 | 0.90 | 0.38    | 0.56 | 7/8   | 13/16 |





### Male Elbow

|         | Т     | P-NPT     |      |      |      |               |      | E             |      |       |         |
|---------|-------|-----------|------|------|------|---------------|------|---------------|------|-------|---------|
| Duolok  | Tube  | Male Pipe |      |      |      |               |      | Minimum       | F    |       |         |
| Part #  | O.D   | Size      | Α    | Bx   | Ву   | С             | D    | Opening       | Min. | G     | н       |
| D1ME1   | 1/16  | 1/16      | 0.75 | 0.60 | 0.70 | 0.43          | 0.34 | 0.05          | 0.38 | 5/16  | 7/16    |
| D1ME2   | 1/16  | 1/8       | 0.75 | 0.60 | 0.70 | 0.43          | 0.34 | 0.05          | 0.38 | 5/16  | 1/2     |
| D2ME1   | 1/8   | 1/16      | 0.93 | 0.67 | 0.70 | 0.60          | 0.50 | 0.09          | 0.38 | 7/16  | 7/16    |
| D2ME2   | 1/8   | 1/8       | 0.93 | 0.67 | 0.70 | 0.60          | 0.50 | 0.09          | 0.38 | 7/16  | 7/16    |
| D2ME4   | 1/8   | 1/4       | 0.97 | 0.71 | 0.92 | 0.60          | 0.50 | 0.09          | 0.56 | 7/16  | 1/2     |
| D3ME2   | 3/16  | 1/8       | 1.00 | 0.74 | 0.74 | 0.63          | 0.54 | 0.12          | 0.38 | 1/2   | 1/2     |
| D3ME4   | 3/16  | 1/4       | 1.00 | 0.74 | 0.92 | 0.63          | 0.54 | 0.12          | 0.56 | 1/2   | 1/2     |
| D4ME2   | 1/4   | 1/8       | 1.06 | 0.77 | 0.74 | 0.70          | 0.60 | 0.17          | 0.38 | 9/16  | 1/2     |
| D4ME4   | 1/4   | 1/4       | 1.06 | 0.77 | 0.92 | 0.70          | 0.60 | 0.19          | 0.56 | 9/16  | 1/2     |
| D4ME6   | 1/4   | 3/8       | 1.17 | 0.88 | 1.03 | 0.70          | 0.60 | 0.19          | 0.56 | 9/16  | 11/16   |
| D4ME8   | 1/4   | 1/2       | 1.25 | 0.96 | 1.30 | 0.70          | 0.60 | 0.19          | 0.75 | 9/16  | 7/8     |
| D5ME2   | 5/16  | 1/8       | 1.13 | 0.84 | 0.78 | 0.73          | 0.64 | 0.19          | 0.38 | 5/8   | 9/16    |
| D5ME4   | 5/16  | 1/4       | 1.13 | 0.84 | 0.96 | 0.73          | 0.64 | 0.25          | 0.56 | 5/8   | 9/16    |
| D5ME6   | 5/16  | 3/8       | 1.20 | 0.91 | 1.03 | 0.73          | 0.64 | 0.25          | 0.56 | 5/8   | 11/16   |
| D6ME2   | 3/8   | 1/8       | 1.20 | 0.91 | 0.82 | 0.76          | 0.66 | 0.19          | 0.38 | 11/16 | 5/8     |
| D6ME4   | 3/8   | 1/4       | 1.20 | 0.91 | 1.00 | 0.76          | 0.66 | 0.28          | 0.56 | 11/16 | 5/8     |
| D6ME6   | 3/8   | 3/8       | 1.23 | 0.94 | 1.03 | 0.76          | 0.66 | 0.28          | 0.56 | 11/16 | 11/16   |
| D6ME8   | 3/8   | 1/2       | 1.31 | 1.02 | 1.30 | 0.76          | 0.66 | 0.28          | 0.75 | 11/16 | 7/8     |
| D6ME12  | 3/8   | 3/4       | 1.46 | 1.17 | 1.45 | 0.76          | 0.66 | 0.28          | 0.75 | 11/16 | 1-1/16  |
| D8ME4   | 1/2   | 1/4       | 1.42 | 1.02 | 1.11 | 0.86          | 0.90 | 0.28          | 0.56 | 7/8   | 13/16   |
| D8ME6   | 1/2   | 3/8       | 1.42 | 1.02 | 1.11 | 0.86          | 0.90 | 0.38          | 0.56 | 7/8   | 13/16   |
| D8ME8   | 1/2   | 1/2       | 1.42 | 1.02 | 1.30 | 0.86          | 0.90 | 0.41          | 0.75 | 7/8   | 7/8     |
| D8ME12  | 1/2   | 3/4       | 1.57 | 1.17 | 1.45 | 0.86          | 0.90 | 0.41          | 0.75 | 7/8   | 1-1/16  |
| D10ME6  | 5/8   | 3/8       | 1.50 | 1.10 | 1.19 | 0.86          | 0.96 | 0.38          | 0.56 | 1     | 15/16   |
| D10ME8  | 5/8   | 1/2       | 1.50 | 1.10 | 1.38 | 0.86          | 0.96 | 0.47          | 0.75 | 1     | 15/16   |
| D10ME12 | 5/8   | 3/4       | 1.57 | 1.17 | 1.45 | 0.86          | 0.96 | 0.50          | 0.75 | 1     | 1-1/16  |
| D12ME8  | 3/4   | 1/2       | 1.57 | 1.17 | 1.45 | 0.86          | 0.96 | 0.47          | 0.75 | 1-1/8 | 1-1/16  |
| D12ME12 | 3/4   | 3/4       | 1.57 | 1.17 | 1.45 | 0.86          | 0.96 | 0.62          | 0.75 | 1-1/8 | 1-1/16  |
| D14ME12 | 7/8   | 3/4       | 1.76 | 1.36 | 1.64 | 0.86          | 1.02 | 0.62          | 0.75 | 1-1/4 | 1-3/8   |
| D16ME12 | 1     | 3/4       | 1.93 | 1.45 | 1.64 | 1.04          | 1.23 | 0.62          | 0.75 | 1-1/2 | 1-3/8   |
| D16ME16 | 1     | 1         | 1.93 | 1.45 | 1.83 | 1.04          | 1.23 | 0.88          | 0.94 | 1-1/2 | 1-3/8   |
| D20ME20 | 1-1/4 | 1-1/4     | 2.62 | 1.75 | 1.88 | 1.53          | 1.62 | 1.09          | 0.94 | 1-7/8 | 1-11/16 |
| D24ME24 | 1-1/2 | 1-1/2     | 3.07 | 2.00 | 2.38 | 1.78          | 1.97 | 1.34          | 1.06 | 2-1/4 | 2       |
| D32ME32 | 2     | 2         | 4.22 | 2.75 | 2.78 | 2 <u>.</u> 47 | 2.66 | 1 <u>.</u> 81 | 1.06 | 3     | 2-3/4   |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.





### Male Elbow - ISO Tapered

|         | Т    | Р         |      |      |      |      | E       | н      | G     |      |      |
|---------|------|-----------|------|------|------|------|---------|--------|-------|------|------|
| Duolok  | Tube | ISO       |      |      |      |      | Min.    | Wrench | Hex   |      |      |
| Part #  | O.D. | Male Pipe | Α    | F    | С    | D    | Opening | Pad    | Flat  | Вx   | Ву   |
| D2MERT2 | 1/8  | 1/8       | 0.93 | 0.38 | 0.60 | 0.50 | 0.09    | 7/16   | 7/16  | 0.67 | 0.70 |
| D4MERT2 | 1/4  | 1/8       | 1.06 | 0.38 | 0.70 | 0.60 | 0.19    | 1/2    | 9/16  | 0.77 | 0.74 |
| D4MERT4 | 1/4  | 1/4       | 1.06 | 0.56 | 0.70 | 0.60 | 0.19    | 1/2    | 9/16  | 0.77 | 0.92 |
| D4MERT6 | 1/4  | 3/8       | 1.17 | 0.56 | 0.70 | 0.60 | 0.19    | 11/16  | 9/16  | 0.88 | 1.03 |
| D4MERT8 | 1/4  | 1/2       | 1.25 | 0.75 | 0.70 | 0.60 | 0.19    | 13/16  | 9/16  | 0.96 | 1.30 |
| D5MERT4 | 5/16 | 1/4       | 1.13 | 0.56 | 0.73 | 0.64 | 0.25    | 9/16   | 5/8   | 0.84 | 0.96 |
| D6MERT2 | 3/8  | 1/8       | 1.20 | 0.38 | 0.76 | 0.66 | 0.19    | 5/8    | 11/16 | 0.91 | 0.82 |
| D6MERT4 | 3/8  | 1/4       | 1.20 | 0.56 | 0.76 | 0.66 | 0.28    | 5/8    | 11/16 | 0.91 | 1.00 |
| D6MERT6 | 3/8  | 3/8       | 1.23 | 0.56 | 0.76 | 0.66 | 0.28    | 11/16  | 11/16 | 0.94 | 1.03 |
| D6MERT8 | 3/8  | 1/2       | 1.31 | 0.75 | 0.76 | 0.66 | 0.28    | 13/16  | 11/16 | 1.02 | 1.30 |
| D8MERT4 | 1/2  | 1/4       | 1.42 | 0.56 | 0.86 | 0.90 | 0.28    | 13/16  | 7/8   | 1.02 | 1.11 |
| D8MERT6 | 1/2  | 3/8       | 1.42 | 0.56 | 0.86 | 0.90 | 0.38    | 13/16  | 7/8   | 1.02 | 1.11 |
| D8MERT8 | 1/2  | 1/2       | 1.42 | 0.75 | 0.86 | 0.90 | 0.41    | 13/16  | 7/8   | 1.02 | 1.30 |

NOTE: RT threaded fittings conform to ISO (International Standards Organization) standards 7/1.

Always specify genuine Duolok tube fittings.





### Male Branch Tee

|          | Т    | P-NPT     |      |      |      |      |      |      |      | Е       |      |       |        |
|----------|------|-----------|------|------|------|------|------|------|------|---------|------|-------|--------|
| Duolok   | Tube | Male Pipe |      |      |      |      |      |      |      | Minimum | F    |       |        |
| Part #   | O.D. | Size      | Α    | Ax   | В    | Вx   | Ву   | С    | D    | Opening | Min. | G     | Н      |
| D2MBT2   | 1/8  | 1/8       | 1.86 | 0.93 | 1.34 | 0.67 | 0.70 | 0.60 | 0.50 | 0.09    | 0.38 | 7/16  | 7/16   |
| D2MBT4   | 1/8  | 1/4       | 1.94 | 0.97 | 1.42 | 0.71 | 0.92 | 0.60 | 0.50 | 0.09    | 0.56 | 7/16  | 9/16   |
| D3MBT2   | 3/16 | 1/8       | 1.92 | 0.96 | 1.40 | 0.70 | 0.70 | 0.63 | 0.54 | 0.12    | 0.38 | 1/2   | 7/16   |
| D4MBT2   | 1/4  | 1/8       | 2.12 | 1.06 | 1.54 | 0.77 | 0.74 | 0.70 | 0.60 | 0.17    | 0.38 | 9/16  | 1/2    |
| D4MBT4   | 1/4  | 1/4       | 2.12 | 1.06 | 1.54 | 0.77 | 0.92 | 0.70 | 0.60 | 0.17    | 0.56 | 9/16  | 9/16   |
| D5MBT2   | 5/16 | 1/8       | 2.34 | 1.17 | 1.76 | 0.88 | 0.82 | 0.73 | 0.64 | 0.19    | 0.38 | 5/8   | 5/8    |
| D6MBT4   | 3/8  | 1/4       | 2.40 | 1.20 | 1.82 | 0.91 | 1.00 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 5/8    |
| D6MBT6   | 3/8  | 3/8       | 2.62 | 1.31 | 2.04 | 1.02 | 1.11 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 13/16  |
| D8MBT6   | 1/2  | 3/8       | 2.84 | 1.42 | 2.04 | 1.02 | 1.11 | 0.86 | 0.90 | 0.38    | 0.56 | 7/8   | 13/16  |
| D8MBT8   | 1/2  | 1/2       | 2.84 | 1.42 | 2.04 | 1.02 | 1.30 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 7/8    |
| D10MBT8  | 5/8  | 1/2       | 3.06 | 1.53 | 2.26 | 1.13 | 1.41 | 0.86 | 0.96 | 0.47    | 0.75 | 1     | 1      |
| D12MBT12 | 3/4  | 3/4       | 3.14 | 1.57 | 2.34 | 1.17 | 1.45 | 0.86 | 0.96 | 0.62    | 0.75 | 1-1/8 | 1-1/16 |





### Male Run Tee

|          | Т    | P-NPT     |      |      |      |      |      |      |      | Е       |      |       |        |
|----------|------|-----------|------|------|------|------|------|------|------|---------|------|-------|--------|
| Duolok   | Tube | Male Pipe |      |      |      |      |      |      |      | Minimum | F    |       |        |
| Part #   | O.D. | Size      | Α    | Ax   | В    | Вx   | Ву   | С    | D    | Opening | Min. | G     | н      |
| D2MRT2   | 1/8  | 1/8       | 1.63 | 0.93 | 1.37 | 0.67 | 0.70 | 0.60 | 0.50 | 0.09    | 0.38 | 7/16  | 7/16   |
| D2MRT4   | 1/8  | 1/4       | 1.89 | 0.97 | 1.63 | 0.71 | 0.92 | 0.60 | 0.50 | 0.09    | 0.56 | 7/16  | 9/16   |
| D3MRT2   | 3/16 | 1/8       | 1.66 | 0.96 | 1.40 | 0.70 | 0.70 | 0.63 | 0.54 | 0.12    | 0.38 | 1/2   | 7/16   |
| D4MRT2   | 1/4  | 1/8       | 1.80 | 1.06 | 1.51 | 0.77 | 0.74 | 0.70 | 0.60 | 0.17    | 0.38 | 9/16  | 1/2    |
| D4MRT4   | 1/4  | 1/4       | 1.98 | 1.06 | 1.69 | 0.77 | 0.92 | 0.70 | 0.60 | 0.19    | 0.56 | 9/16  | 9/16   |
| D5MRT2   | 5/16 | 1/8       | 1.99 | 1.17 | 1.70 | 0.88 | 0.82 | 0.73 | 0.64 | 0.19    | 0.38 | 5/8   | 5/8    |
| D6MRT4   | 3/8  | 1/4       | 2.20 | 1.20 | 1.91 | 0.91 | 1.00 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 5/8    |
| D6MRT6   | 3/8  | 3/8       | 2.42 | 1.31 | 2.13 | 1.02 | 1.11 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 13/16  |
| D8MRT6   | 1/2  | 3/8       | 2.53 | 1.42 | 2.13 | 1.02 | 1.11 | 0.86 | 0.90 | 0.38    | 0.56 | 7/8   | 13/16  |
| D8MRT8   | 1/2  | 1/2       | 2.72 | 1.42 | 2.32 | 1.02 | 1.30 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 7/8    |
| D10MRT8  | 5/8  | 1/2       | 2.88 | 1.50 | 2.48 | 1.10 | 1.38 | 0.86 | 0.96 | 0.47    | 0.75 | 1     | 1      |
| D12MRT12 | 3/4  | 3/4       | 3.02 | 1.57 | 2.62 | 1.17 | 1.45 | 0.86 | 0.96 | 0.62    | 0.75 | 1-1/8 | 1-1/16 |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.





### Female Connector

|         | Т     | P-NPT       |      |      |      |      | E       |       |        |
|---------|-------|-------------|------|------|------|------|---------|-------|--------|
| Duolok  | Tube  | Female Pipe |      |      |      |      | Minimum |       |        |
| Part #  | O.D.  | Size        | A    | В    | С    | D    | Opening | G     | н      |
| D1FC1   | 1/16  | 1/16        | 0.93 | 0.78 | 0.43 | 0.34 | 0.05    | 5/16  | 7/16   |
| D1FC2   | 1/16  | 1/8         | 0.96 | 0.81 | 0.43 | 0.34 | 0.05    | 5/16  | 9/16   |
| D2FC2   | 1/8   | 1/8         | 1.13 | 0.87 | 0.60 | 0.50 | 0.09    | 7/16  | 9/16   |
| D2FC4   | 1/8   | 1/4         | 1.32 | 1.06 | 0.60 | 0.50 | 0.09    | 7/16  | 3/4    |
| D3FC2   | 3/16  | 1/8         | 1.17 | 0.91 | 0.63 | 0.54 | 0.12    | 1/2   | 9/16   |
| D4FC2   | 1/4   | 1/8         | 1.23 | 0.94 | 0.70 | 0.60 | 0.19    | 9/16  | 9/16   |
| D4FC4   | 1/4   | 1/4         | 1.41 | 1.12 | 0.70 | 0.60 | 0.19    | 9/16  | 3/4    |
| D4FC6   | 1/4   | 3/8         | 1.48 | 1 19 | 0.70 | 0.60 | 0.19    | 9/16  | 7/8    |
| D4FC8   | 1/4   | 1/2         | 1.67 | 1.38 | 0.70 | 0.60 | 0.19    | 9/16  | 1-1/16 |
| D5FC2   | 5/16  | 1/8         | 1.26 | 0.97 | 0.73 | 0.64 | 0.25    | 5/8   | 9/16   |
| D5FC4   | 5/16  | 1/4         | 1.45 | 1.16 | 0.73 | 0.64 | 0.25    | 5/8   | 3/4    |
| D6FC2   | 3/8   | 1/8         | 1.29 | 1.00 | 0.76 | 0.66 | 0.28    | 11/16 | 5/8    |
| D6FC4   | 3/8   | 1/4         | 1.48 | 1.19 | 0.76 | 0.66 | 0.28    | 11/16 | 3/4    |
| D6FC6   | 3/8   | 3/8         | 1.54 | 1.25 | 0.76 | 0.66 | 0.28    | 11/16 | 7/8    |
| D6FC8   | 3/8   | 1/2         | 1.73 | 1.44 | 0.76 | 0.66 | 0.28    | 11/16 | 1-1/16 |
| D6FC12  | 3/8   | 3/4         | 1.88 | 1.59 | 0.76 | 0.66 | 0.28    | 11/16 | 1-5/16 |
| D8FC4   | 1/2   | 1/4         | 1.59 | 1.19 | 0.86 | 0.90 | 0.41    | 7/8   | 13/16  |
| D8FC6   | 1/2   | 3/8         | 1.65 | 1.25 | 0.86 | 0.90 | 0.41    | 7/8   | 7/8    |
| D8FC8   | 1/2   | 1/2         | 1.84 | 1.44 | 0.86 | 0.90 | 0.41    | 7/8   | 1-1/16 |
| D8FC12  | 1/2   | 3/4         | 1.90 | 1.50 | 0.86 | 0.90 | 0.41    | 7/8   | 1-5/16 |
| D10FC6  | 5/8   | 3/8         | 1.65 | 1.25 | 0.86 | 0.96 | 0.50    | 1     | 15/16  |
| D10FC8  | 5/8   | 1/2         | 1.84 | 1.44 | 0.86 | 0.96 | 0.50    | 1     | 1-1/16 |
| D12FC8  | 3/4   | 1/2         | 1.84 | 1.44 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-1/16 |
| D12FC12 | 3/4   | 3/4         | 1.90 | 1.50 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-5/16 |
| D14FC12 | 7/8   | 3/4         | 1.96 | 1.56 | 0.86 | 1.02 | 0.72    | 1-1/4 | 1-5/16 |
| D16FC12 | 1     | 3/4         | 2.10 | 1.62 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-3/8  |
| D16FC16 | 1     | 1           | 2.45 | 1.97 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-5/8  |
| D20FC20 | 1-1/4 | 1-1/4       | 2.94 | 2.07 | 1.53 | 1.62 | 1.09    | 1-7/8 | 2-1/8  |
| D24FC24 | 1-1/2 | 1-1/2       | 3.28 | 2.21 | 1.78 | 1.97 | 1.34    | 1-1/4 | 2-3/8  |
| D32FC32 | 2     | 2           | 4.00 | 2.53 | 2.47 | 2.66 | 1.81    | 3     | 2-7/8  |





### **Bulkhead Female Connector**

|        | Т    | P-NPT       |      |      |      |      |      | Е       |       |        |       | Maximum   | Panel      |
|--------|------|-------------|------|------|------|------|------|---------|-------|--------|-------|-----------|------------|
| Duolok | Tube | Female Pipe |      |      |      |      |      | Minimum |       |        |       | Panel     | Hole Drill |
| Part # | O.D. | Size        | Α    | Ax   | В    | Вx   | D    | Opening | G     | н      | Hx    | Thickness | Size       |
| D2BFC2 | 1/8  | 1/8         | 1.76 | 1.23 | 1.50 | 0.97 | 0.50 | 0.09    | 7/16  | 9/16   | 1/2   | 0.50      | 21/64      |
| D4BFC2 | 1/4  | 1/8         | 1.85 | 1.32 | 1.56 | 1.03 | 0.60 | 0.19    | 9/16  | 5/8    | 5/8   | 0.40      | 29/64      |
| D4BFC4 | 1/4  | 1/4         | 2.04 | 1.32 | 1.75 | 1.03 | 0.60 | 0.19    | 9/16  | 3/4    | 5/8   | 0.40      | 29/64      |
| D6BFC4 | 3/8  | 1/4         | 2.17 | 1.45 | 1.88 | 1.16 | 0.66 | 0.28    | 11/16 | 3/4    | 3/4   | 0.44      | 37/64      |
| D8BFC6 | 1/2  | 3/8         | 2.43 | 1.65 | 2.03 | 1.25 | 0.90 | 0.41    | 7/8   | 15/16  | 15/16 | 0.50      | 49/64      |
| D8BFC8 | 1/2  | 1/2         | 2.62 | 1.65 | 2.22 | 1.25 | 0.90 | 0.41    | 7/8   | 1-1/16 | 15/16 | 0.50      | 49/64      |

Duolok products are readily available from factory authorized distributors.

20





### Female Run Tee

|          | Т    | P-NPT       |      |      |      |      |      |      |      | Е       |       |        |
|----------|------|-------------|------|------|------|------|------|------|------|---------|-------|--------|
| Duolok   | Tube | Female Pipe |      |      |      |      |      |      |      | Minimum |       |        |
| Part #   | O.D. | Size        | Α    | Ax   | В    | Bx   | Ву   | С    | D    | Opening | G     | н      |
| D2FRT2   | 1/8  | 1/8         | 1.72 | 0.97 | 1.46 | 0.71 | 0.75 | 0.60 | 0.50 | 0.09    | 7/16  | 9/16   |
| D4FRT2   | 1/4  | 1/8         | 1.81 | 1.06 | 1.52 | 0.77 | 0.75 | 0.70 | 0.60 | 0.19    | 9/16  | 9/16   |
| D4FRT4   | 1/4  | 1/4         | 2.05 | 1.17 | 1.76 | 0.88 | 0.88 | 0.70 | 0.60 | 0.19    | 9/16  | 3/4    |
| D6FRT4   | 3/8  | 1/4         | 2.11 | 1.23 | 1.82 | 0.94 | 0.88 | 0.76 | 0.66 | 0.28    | 11/16 | 3/4    |
| D8FRT6   | 1/2  | 3/8         | 2.30 | 1.42 | 1.90 | 1.02 | 0.88 | 0.86 | 0.90 | 0.41    | 7/8   | 7/8    |
| D8FRT8   | 1/2  | 1/2         | 2.69 | 1.57 | 2.29 | 1.17 | 1.12 | 0.86 | 0.90 | 0.41    | 7/8   | 1-1/16 |
| D12FRT12 | 3/4  | 3/4         | 3.01 | 1.76 | 2.61 | 1.36 | 1.25 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-3/8  |

See page 9 for the safe, simple installation instructions for Duolok tube fittings.





### Female Elbow

|         | Т    | P-NPT       |      |      |      |      |      | Е       |       |        |
|---------|------|-------------|------|------|------|------|------|---------|-------|--------|
| Duolok  | Tube | Female Pipe |      |      |      |      |      | Minimum |       |        |
| Part #  | O.D. | Size        | Α    | Вx   | Ву   | С    | D    | Opening | G     | н      |
| D2FE2   | 1/8  | 1/8         | 0.97 | 0.71 | 0.75 | 0.60 | 0.50 | 0.09    | 7/16  | 1/2    |
| D2FE4   | 1/8  | 1/4         | 1.08 | 0.82 | 0.88 | 0.60 | 0.50 | 0.09    | 7/16  | 11/16  |
| D3FE2   | 3/16 | 1/8         | 1.00 | 0.74 | 0.75 | 0.63 | 0.54 | 0.12    | 1/2   | 1/2    |
| D4FE2   | 1/4  | 1/8         | 1.06 | 0.77 | 0.75 | 0.70 | 0.60 | 0.19    | 9/16  | 1/2    |
| D4FE4   | 1/4  | 1/4         | 1.17 | 0.88 | 0.88 | 0.70 | 0.60 | 0.19    | 9/16  | 11/16  |
| D4FE6   | 1/4  | 3/8         | 1.25 | 0.96 | 0.88 | 0.70 | 0.60 | 0.19    | 9/16  | 7/8    |
| D4FE8   | 1/4  | 1/2         | 1.36 | 1.07 | 1.12 | 0.70 | 0.60 | 0.19    | 9/16  | 1      |
| D5FE2   | 5/16 | 1/8         | 1.13 | 0.84 | 0.75 | 0.73 | 0.64 | 0.25    | 5/8   | 9/16   |
| D5FE4   | 5/16 | 1/4         | 1.20 | 0.91 | 0.88 | 0.73 | 0.64 | 0.25    | 5/8   | 11/16  |
| D6FE2   | 3/8  | 1/8         | 1.20 | 0.91 | 0.75 | 0.76 | 0.66 | 0.28    | 11/16 | 5/8    |
| D6FE4   | 3/8  | 1/4         | 1.23 | 0.94 | 0.88 | 0.76 | 0.66 | 0.28    | 11/16 | 11/16  |
| D6FE6   | 3/8  | 3/8         | 1.31 | 1.02 | 0.88 | 0.76 | 0.66 | 0.28    | 11/16 | 7/8    |
| D6FE8   | 3/8  | 1/2         | 1.42 | 1.13 | 1.12 | 0.76 | 0.66 | 0.28    | 11/16 | 1      |
| D8FE4   | 1/2  | 1/4         | 1.42 | 1.02 | 0.88 | 0.86 | 0.90 | 0.41    | 7/8   | 13/16  |
| D8FE6   | 1/2  | 3/8         | 1.42 | 1.02 | 0.88 | 0.86 | 0.90 | 0.41    | 7/8   | 7/8    |
| D8FE8   | 1/2  | 1/2         | 1.53 | 1.13 | 1.12 | 0.86 | 0.90 | 0.41    | 7/8   | 1      |
| D10FE6  | 5/8  | 3/8         | 1.50 | 1.10 | 0.88 | 0.86 | 0.96 | 0.50    | 1     | 15/16  |
| D10FE8  | 5/8  | 1/2         | 1.57 | 1.17 | 1.12 | 0.86 | 0.96 | 0.50    | 1     | 1-1/16 |
| D12FE8  | 3/4  | 1/2         | 1.57 | 1.17 | 1.12 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-1/16 |
| D12FE12 | 3/4  | 3/4         | 1.76 | 1.36 | 1.25 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-3/8  |
| D14FE12 | 7/8  | 3/4         | 1.76 | 1.36 | 1.25 | 0.86 | 1.02 | 0.72    | 1-1/4 | 1-3/8  |
| D16FE12 | 1    | 3/4         | 1.93 | 1.45 | 1.25 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-3/8  |
| D16FE16 | 1    | 1           | 2.11 | 1.63 | 1.50 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-5/8  |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

## Tube to Female Pipe / Tube to Tube Union





### Female Branch Tee

|          | Т    | P-NPT     |      |      |      |      |      |      |      | E       |       |       |
|----------|------|-----------|------|------|------|------|------|------|------|---------|-------|-------|
| Duolok   | Tube | Female    |      |      |      |      |      |      |      | Minimum |       |       |
| Part #   | O.D. | Pipe Size | Α    | Ax   | В    | Bx   | Ву   | С    | D    | Opening | G     | Н     |
| D2FBT2   | 1/8  | 1/8       | 1.94 | 0.97 | 1.42 | 0.71 | 0.75 | 0.60 | 0.50 | 0.09    | 7/16  | 9/16  |
| D4FBT2   | 1/4  | 1/8       | 2.12 | 1.06 | 1.54 | 0.77 | 0.75 | 0.70 | 0.60 | 0.19    | 9/16  | 9/16  |
| D4FBT4   | 1/4  | 1/4       | 2.34 | 1.17 | 1.76 | 0.88 | 0.88 | 0.70 | 0.60 | 0.19    | 9/16  | 3/4   |
| D6FBT4   | 3/8  | 1/4       | 2.46 | 1.23 | 1.88 | 0.94 | 0.88 | 0.76 | 0.66 | 0.28    | 11/16 | 3/4   |
| D8FBT4   | 1/2  | 1/4       | 2.84 | 1.42 | 2.04 | 1.02 | 0.88 | 0.86 | 0.90 | 0.41    | 7/8   | 13/16 |
| D8FBT6   | 1/2  | 3/8       | 2.84 | 1.42 | 2.04 | 1.02 | 0.88 | 0.86 | 0.90 | 0.41    | 7/8   | 7/8   |
| D8FBT8   | 1/2  | 1/2       | 3.06 | 1.53 | 2.26 | 1.13 | 1.12 | 0.86 | 0.90 | 0.41    | 7/8   | 1     |
| D10FBT8  | 5/8  | 1/2       | 3.06 | 1.53 | 2.26 | 1.13 | 1.12 | 0.86 | 0.96 | 0.50    | 1     | 1     |
| D12FBT12 | 3/4  | 3/4       | 3.52 | 1.76 | 2.72 | 1.36 | 1.25 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-3/8 |
| D16FBT12 | 1    | 3/4       | 3.86 | 1.93 | 2.90 | 1.45 | 1.25 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-3/8 |
| D16FBT16 | 1    | 1         | 4.22 | 2.11 | 3.26 | 1.63 | 1.50 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-5/8 |





### Union

|        | Т     |               |      |      |      | E       |       |        |
|--------|-------|---------------|------|------|------|---------|-------|--------|
| Duolok | Tube  |               |      |      |      | Minimum |       |        |
| Part # | O.D.  | Α             | в    | С    | D    | Opening | G     | н      |
| D1U    | 1/16  | 0.99          | 0.69 | 0.43 | 0.34 | 0.05    | 5/16  | 5/16   |
| D2U    | 1/8   | 1.40          | 0.88 | 0.60 | 0.50 | 0.09    | 7/16  | 7/16   |
| D3U    | 3/16  | 1 <u>.</u> 47 | 0.95 | 0.63 | 0.54 | 0.12    | 1/2   | 7/16   |
| D4U    | 1/4   | 1.61          | 1.03 | 0.70 | 0.60 | 0.19    | 9/16  | 1/2    |
| D5U    | 5/16  | 1.69          | 1.11 | 0.73 | 0.64 | 0.25    | 5/8   | 9/16   |
| D6U    | 3/8   | 1.77          | 1.19 | 0.76 | 0.66 | 0.28    | 11/16 | 5/8    |
| D8U    | 1/2   | 2.02          | 1.22 | 0.86 | 0.90 | 0.41    | 7/8   | 13/16  |
| D10U   | 5/8   | 2.05          | 1.25 | 0.86 | 0.96 | 0.50    | 1     | 15/16  |
| D12U   | 3/4   | 2.11          | 1.31 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-1/16 |
| D14U   | 7/8   | 2.17          | 1.37 | 0.86 | 1.02 | 0.72    | 1-1/4 | 1-3/16 |
| D16U   | 1     | 2.55          | 1.59 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-3/8  |
| D20U   | 1-1/4 | 2.63          | 1.89 | 1.53 | 1.62 | 1.09    | 1-7/8 | 1-3/4  |
| D24U   | 1-1/2 | 4.25          | 2.11 | 1.78 | 1.97 | 1.34    | 2-1/4 | 2-1/8  |
| D32U   | 2     | 5.88          | 2.94 | 2.47 | 2.66 | 1.81    | 3     | 2-3/4  |

*Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.* **When ordering, specify material designator with part number (see page 3 for complete ordering information).** 





### **Bulkhead Union**

| Duolok | T    |      |      |      |      |      |      | E<br>Minimum |       |        | Maximum<br>Panel | Panel<br>Hole Drill |
|--------|------|------|------|------|------|------|------|--------------|-------|--------|------------------|---------------------|
| Part # | O.D. | Α    | Ax   | в    | Вx   | с    | D    | Opening      | G     | н      | Thickness        | Size                |
| D1BU   | 1/16 | 1.24 | 0.68 | 0.94 | 0.53 | 0.43 | 0.34 | 0.05         | 5/16  | 5/16   | 0.12             | 13/64               |
| D2BU   | 1/8  | 2.02 | 1.23 | 1.50 | 0.97 | 0.60 | 0.50 | 0.09         | 7/16  | 1/2    | 0.50             | 21/64               |
| D3BU   | 3/16 | 2.11 | 1.26 | 1.59 | 1.00 | 0.63 | 0.54 | 0.12         | 1/2   | 9/16   | 0.50             | 25/64               |
| D4BU   | 1/4  | 2.27 | 1.32 | 1.69 | 1.03 | 0.70 | 0.60 | 0.19         | 9/16  | 5/8    | 0.40             | 29/64               |
| D5BU   | 5/16 | 2.39 | 1.41 | 1.81 | 1.12 | 0.73 | 0.64 | 0.25         | 5/8   | 11/16  | 0.44             | 33/64               |
| D6BU   | 3/8  | 2.45 | 1.45 | 1.87 | 1.16 | 0.76 | 0.66 | 0.28         | 11/16 | 3/4    | 0.44             | 37/64               |
| D8BU   | 1/2  | 2.80 | 1.65 | 2.00 | 1.25 | 0.86 | 0.90 | 0.41         | 7/8   | 15/16  | 0.50             | 49/64               |
| D10BU  | 5/8  | 2.86 | 1.68 | 2.06 | 1.28 | 0.86 | 0.96 | 0.50         | 1     | 1-1/16 | 0.50             | 57/64               |
| D12BU  | 3/4  | 3.11 | 1.87 | 2.31 | 1.47 | 0.86 | 0.96 | 0.63         | 1-1/8 | 1-3/16 | 0.66             | 1-1/64              |
| D16BU  | 1    | 3.77 | 2.26 | 2.81 | 1.78 | 1.04 | 1.23 | 0.88         | 1-1/2 | 1-5/8  | 0.75             | 1-21/64             |





### Bulkhead Reducing Union

24

|        | Т    | Тх   |      |      |      |      |      |      |      | E       |       |       |       |       | Maximum   | Panel      |
|--------|------|------|------|------|------|------|------|------|------|---------|-------|-------|-------|-------|-----------|------------|
| Duolok | Tube | Tube |      |      |      |      |      |      |      | Minimum |       |       |       |       | Panel     | Hole       |
| Part # | O.D. | O.D. | Α    | Ax   | В    | Bx   | Cx   | D    | Dx   | Opening | G     | Gx    | н     | Hx    | Thickness | Drill Size |
| D4BRU2 | 1/4  | 1/8  | 2.17 | 1.32 | 1.62 | 1.03 | 0.60 | 0.60 | 0.50 | 0.09    | 9/16  | 7/16  | 5/8   | 5/8   | 0.40      | 29/64      |
| D6BRU4 | 3/8  | 1/4  | 2.39 | 1.44 | 1.81 | 1.16 | 0.70 | 0.66 | 0.60 | 0.19    | 11/16 | 9/16  | 3/4   | 3/4   | 0.44      | 37/64      |
| D8BRU4 | 1/2  | 1/4  | 2.63 | 1.65 | 1.94 | 1.25 | 0.70 | 0.90 | 0.60 | 0.19    | 7/8   | 9/16  | 15/16 | 15/16 | 0.50      | 49/64      |
| D8BRU6 | 1/2  | 3/8  | 2.68 | 1.65 | 1.99 | 1.25 | 0.75 | 0.90 | 0.66 | 0.19    | 7/8   | 11/16 | 15/16 | 15/16 | 0.50      | 49/64      |





### **Reducing Union**

|         | Т    | Тх   |      |      |      |      |      |      | Е       |       |       |        |
|---------|------|------|------|------|------|------|------|------|---------|-------|-------|--------|
| Duolok  | Tube | Tube |      |      |      |      |      |      | Minimum |       |       |        |
| Part #  | O.D. | O.D. | A    | в    | С    | Сх   | D    | Dx   | Opening | G     | Gx    | н      |
| D2RU1   | 1/8  | 1/16 | 1.22 | 0.81 | 0.60 | 0.43 | 0.50 | 0.34 | 0.05    | 7/16  | 5/16  | 7/16   |
| D3RU1   | 3/16 | 1/16 | 1.27 | 0.86 | 0.63 | 0.43 | 0.54 | 0.34 | 0.05    | 1/2   | 5/16  | 7/16   |
| D3RU2   | 3/16 | 1/8  | 1.44 | 0.92 | 0.63 | 0.60 | 0.54 | 0.50 | 0.09    | 1/2   | 7/16  | 7/16   |
| D4RU1   | 1/4  | 1/16 | 1.35 | 0.91 | 0.70 | 0.43 | 0.60 | 0.34 | 0.05    | 9/16  | 5/16  | 1/2    |
| D4RU2   | 1/4  | 1/8  | 1.52 | 0.97 | 0.70 | 0.60 | 0.60 | 0.50 | 0.09    | 9/16  | 7/16  | 1/2    |
| D4RU3   | 1/4  | 3/16 | 1.55 | 1.00 | 0.70 | 0.63 | 0.60 | 0.54 | 0.12    | 9/16  | 1/2   | 1/2    |
| D5RU2   | 5/16 | 1/8  | 1.57 | 1.02 | 0.73 | 0.60 | 0.64 | 0.50 | 0.09    | 5/8   | 7/16  | 9/16   |
| D5RU4   | 5/16 | 1/4  | 1.66 | 1.08 | 0.73 | 0.70 | 0.64 | 0.60 | 0.19    | 5/8   | 9/16  | 9/16   |
| D6RU1   | 3/8  | 1/16 | 1.44 | 1.00 | 0.76 | 0.43 | 0.66 | 0.34 | 0.05    | 11/16 | 5/16  | 5/8    |
| D6RU2   | 3/8  | 1/8  | 1.61 | 1.06 | 0.76 | 0.60 | 0.66 | 0.50 | 0.09    | 11/16 | 7/16  | 5/8    |
| D6RU4   | 3/8  | 1/4  | 1.70 | 1.12 | 0.76 | 0.70 | 0.66 | 0.60 | 0.19    | 11/16 | 9/16  | 5/8    |
| D6RU5   | 3/8  | 5/16 | 1.74 | 1.16 | 0.76 | 0.73 | 0.66 | 0.64 | 0.25    | 11/16 | 5/8   | 5/8    |
| D8RU2   | 1/2  | 1/8  | 1.78 | 1.12 | 0.86 | 0.60 | 0.90 | 0.50 | 0.09    | 7/8   | 7/16  | 13/16  |
| D8RU4   | 1/2  | 1/4  | 1.85 | 1.16 | 0.86 | 0.70 | 0.90 | 0.60 | 0.19    | 7/8   | 9/16  | 13/16  |
| D8RU6   | 1/2  | 3/8  | 1.91 | 1.22 | 0.86 | 0.76 | 0.90 | 0.66 | 0.28    | 7/8   | 11/16 | 13/16  |
| D10RU6  | 5/8  | 3/8  | 1.94 | 1.25 | 0.86 | 0.76 | 0.96 | 0.66 | 0.28    | 1     | 11/16 | 15/16  |
| D10RU8  | 5/8  | 1/2  | 2.05 | 1.25 | 0.86 | 0.86 | 0.96 | 0.90 | 0.41    | 1     | 7/8   | 15/16  |
| D12RU4  | 3/4  | 1/4  | 1.94 | 1.25 | 0.86 | 0.70 | 0.96 | 0.60 | 0.19    | 1-1/8 | 9/16  | 1-1/16 |
| D12RU6  | 3/4  | 3/8  | 2.00 | 1.31 | 0.86 | 0.76 | 0.96 | 0.66 | 0.28    | 1-1/8 | 11/16 | 1-1/16 |
| D12RU8  | 3/4  | 1/2  | 2.11 | 1.31 | 0.86 | 0.86 | 0.96 | 0.90 | 0.41    | 1-1/8 | 7/8   | 1-1/16 |
| D12RU10 | 3/4  | 5/8  | 2.11 | 1.31 | 0.86 | 0.86 | 0.96 | 0.96 | 0.50    | 1-1/8 | 1     | 1-1/16 |
| D16RU8  | 1    | 1/2  | 2.49 | 1.61 | 1.04 | 0.86 | 1.23 | 0.90 | 0.41    | 1-1/2 | 7/8   | 1-3/8  |
| D16RU12 | 1    | 3/4  | 2.47 | 1.59 | 1.04 | 0.86 | 1.23 | 0.96 | 0.62    | 1-1/2 | 1-1/8 | 1-3/8  |

Safety and installation seminars are available through the factory authorized Duolok tube fittings distributor.



![](_page_25_Figure_2.jpeg)

### Union Elbow

|        | T     |      |      |      |      | E       |       |         |
|--------|-------|------|------|------|------|---------|-------|---------|
| Duolok | Tube  |      |      |      |      | Minimum |       |         |
| Part # | O.D.  | Α    | Bx   | С    | D    | Opening | G     | н       |
| D1UE   | 1/16  | 0.70 | 0.55 | 0.43 | 0.34 | 0.05    | 5/16  | 3/8     |
| D2UE   | 1/8   | 0.88 | 0.62 | 0.60 | 0.50 | 0.09    | 7/16  | 3/8     |
| D3UE   | 3/16  | 1.00 | 0.74 | 0.63 | 0.54 | 0.12    | 1/2   | 1/2     |
| D4UE   | 1/4   | 1.06 | 0.77 | 0.70 | 0.60 | 0.19    | 9/16  | 1/2     |
| D5UE   | 5/16  | 1.13 | 0.84 | 0.73 | 0.64 | 0.25    | 5/8   | 9/16    |
| D6UE   | 3/8   | 1.20 | 0.91 | 0.76 | 0.66 | 0.28    | 11/16 | 5/8     |
| D8UE   | 1/2   | 1.42 | 1.02 | 0.86 | 0.90 | 0.41    | 7/8   | 13/16   |
| D10UE  | 5/8   | 1.50 | 1.10 | 0.86 | 0.96 | 0.50    | 1     | 15/16   |
| D12UE  | 3/4   | 1.57 | 1.17 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-1/16  |
| D14UE  | 7/8   | 1.76 | 1.36 | 0.86 | 1.02 | 0.72    | 1-1/4 | 1-3/8   |
| D16UE  | 1     | 1.93 | 1.45 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-3/8   |
| D20UE  | 1-1/4 | 2.62 | 1.75 | 1.53 | 1.62 | 1.09    | 1-7/8 | 1-11/16 |
| D24UE  | 1-1/2 | 3.07 | 2.00 | 1.78 | 1.97 | 1.34    | 2-1/4 | 2       |
| D32UE  | 2     | 4.22 | 2.75 | 2.47 | 2.66 | 1.81    | 3     | 2-3/4   |

![](_page_25_Figure_5.jpeg)

![](_page_25_Figure_6.jpeg)

### **Union Cross**

| Duolok<br>Part # | T<br>Tube<br>O.D. | А    | Ax   | в    | Bx   | с    | D    | E<br>Minimum<br>Opening | G     | н      |
|------------------|-------------------|------|------|------|------|------|------|-------------------------|-------|--------|
| D2UCS            | 1/8               | 1.76 | 0.88 | 1.24 | 0.62 | 0.60 | 0.50 | 0.09                    | 7/16  | 3/8    |
| D4UCS            | 1/4               | 2.12 | 1.06 | 1.54 | 0.77 | 0.70 | 0.60 | 0.19                    | 9/16  | 1/2    |
| D5UCS            | 5/16              | 2.34 | 1.17 | 1.76 | 0.88 | 0.73 | 0.64 | 0.25                    | 5/8   | 5/8    |
| D6UCS            | 3/8               | 2.40 | 1.20 | 1.82 | 0.91 | 0.76 | 0.66 | 0.28                    | 11/16 | 5/8    |
| D8UCS            | 1/2               | 2.84 | 1.42 | 2.04 | 1.02 | 0.86 | 0.90 | 0.41                    | 7/8   | 13/16  |
| D12UCS           | 3/4               | 3.14 | 1.57 | 2.34 | 1.17 | 0.86 | 0.96 | 0.62                    | 1-1/8 | 1-1/16 |
| D16UCS           | 1                 | 3.86 | 1.93 | 2.90 | 1.45 | 1.04 | 1.23 | 0.88                    | 1-1/2 | 1-5/16 |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

![](_page_26_Figure_1.jpeg)

![](_page_26_Figure_2.jpeg)

### Union Tee

|        | Т     |      |      |      |      |      |      | E       |       |        |
|--------|-------|------|------|------|------|------|------|---------|-------|--------|
| Duolok | Tube  |      |      |      |      |      |      | Minimum |       |        |
| Part # | O.D.  | Α    | Ax   | В    | Bx   | С    | D    | Opening | G     | Н      |
| D1UT   | 1/16  | 1.40 | 0.70 | 1.10 | 0.55 | 0.43 | 0.34 | 0.05    | 5/16  | 3/8    |
| D2UT   | 1/8   | 1.76 | 0.88 | 1.24 | 0.62 | 0.60 | 0.50 | 0.09    | 7/16  | 3/8    |
| D3UT   | 3/16  | 1.92 | 0.96 | 1.40 | 0.70 | 0.63 | 0.54 | 0.12    | 1/2   | 7/16   |
| D4UT   | 1/4   | 2.12 | 1.06 | 1.54 | 0.77 | 0.70 | 0.60 | 0.19    | 9/16  | 1/2    |
| D5UT   | 5/16  | 2.34 | 1.17 | 1.76 | 0.88 | 0.73 | 0.64 | 0.25    | 5/8   | 5/8    |
| D6UT   | 3/8   | 2.40 | 1.20 | 1.82 | 0.91 | 0.76 | 0.66 | 0.28    | 11/16 | 5/8    |
| D8UT   | 1/2   | 2.84 | 1.42 | 2.04 | 1.02 | 0.86 | 0.90 | 0.41    | 7/8   | 13/16  |
| D10UT  | 5/8   | 3.06 | 1.53 | 2.26 | 1.13 | 0.86 | 0.96 | 0.50    | 1     | 1      |
| D12UT  | 3/4   | 3.14 | 1.57 | 2.34 | 1.17 | 0.86 | 0.96 | 0.62    | 1-1/8 | 1-1/16 |
| D14UT  | 7/8   | 3.52 | 1.76 | 2.72 | 1.36 | 0.86 | 1.02 | 0.72    | 1-1/4 | 1-3/8  |
| D16UT  | 1     | 3.86 | 1.93 | 2.90 | 1.45 | 1.04 | 1.23 | 0.88    | 1-1/2 | 1-3/8  |
| D20UT  | 1-1/4 | 5.24 | 2.62 | 3.50 | 1.75 | 1.53 | 1.62 | 1.09    | 1-7/8 | 11/16  |
| D24UT  | 1-1/2 | 6.14 | 3.07 | 4.00 | 2.00 | 1.78 | 1.97 | 1.34    | 2-1/4 | 2      |
| D32UT  | 2     | 8.44 | 4.22 | 5.50 | 2.75 | 2.47 | 2.66 | 1.81    | 3     | 2-3/4  |

### Heat Exchanger Tee

Custom configuration, forged heat exchanger tees can be designed and manufactured by SSP to customers' specific design criteria. Additionally, heat exchanger tees may be assembled by utilizing standard union tees (UT) combined with reducers that have been "bored through" (RBT fittings) to allow the process tube to be inserted into and through the jacketing tube.

![](_page_26_Figure_7.jpeg)

**Note:** Pressure ratings of "bored through" fittings are reduced. For additional information on a specific fitting's rating, contact your local distributor.

![](_page_27_Figure_1.jpeg)

![](_page_27_Figure_2.jpeg)

![](_page_27_Figure_3.jpeg)

![](_page_27_Figure_4.jpeg)

![](_page_27_Figure_5.jpeg)

### Reducing Union Tee - Configuration A

|            | Т    | Тх   |      |      |      |      |      |      |      |      |      |      |      |       |        |        |
|------------|------|------|------|------|------|------|------|------|------|------|------|------|------|-------|--------|--------|
| Duolok     | Tube | Tube |      |      |      |      |      |      |      |      |      |      |      |       |        |        |
| Part #     | O.D. | O.D. | Α    | Ax   | Ау   | В    | Bx   | Ву   | С    | Сх   | D    | Dx   | Е    | G     | Gx     | н      |
| D6RUT64    | 3/8  | 1/4  | 2.40 | 1.20 | 1.14 | 1.82 | 0.91 | 0.85 | 0.76 | 0.70 | 0.66 | 0.60 | 0.19 | 11/16 | 9/16   | 5/8    |
| D8RUT84    | 1/2  | 1/4  | 2.84 | 1.42 | 1.25 | 2.04 | 1.02 | 0.96 | 0.86 | 0.70 | 0.90 | 0.60 | 0.19 | 7/8   | 9/16   | 13/16  |
| D8RUT86    | 1/2  | 3/8  | 2.84 | 1.42 | 1.31 | 2.04 | 1.02 | 1.02 | 0.86 | 0.76 | 0.90 | 0.66 | 0.28 | 7/8   | 11/16  | 13/16  |
| D10RUT106  | 5/8  | 3/8  | 3.06 | 1.53 | 1.42 | 2.26 | 1.13 | 1.13 | 0.86 | 0.76 | 0.96 | 0.66 | 0.28 | 1     | 11/16  | 1      |
| D12RUT126  | 3/4  | 3/8  | 3.14 | 1.57 | 1.46 | 2.34 | 1.17 | 1.17 | 0.86 | 0.76 | 0.96 | 0.66 | 0.28 | 1-1/8 | 11/16  | 1-1/16 |
| D12RUT128  | 3/4  | 1/2  | 3.14 | 1.57 | 1.57 | 2.34 | 1.17 | 1.17 | 0.86 | 0.86 | 0.96 | 0.90 | 0.41 | 1-1/8 | 7/8    | 1-1/16 |
| D16RUT166  | 1    | 3/8  | 3.86 | 1.93 | 1.65 | 2.90 | 1.45 | 1.36 | 1.04 | 0.76 | 1.23 | 0.66 | 0.28 | 1-1/2 | 1-1/16 | 1-3/8  |
| D16RUT168  | 1    | 1/2  | 3.86 | 1.93 | 1.76 | 2.90 | 1.45 | 1.36 | 1.04 | 0.90 | 1.23 | 0.86 | 0.41 | 1-1/2 | 7/8    | 1-3/8  |
| D16RUT1612 | 1    | 3/4  | 3.86 | 1.93 | 1.76 | 2.90 | 1.45 | 1.36 | 1.04 | 0.86 | 1.23 | 0.96 | 0.62 | 1-1/2 | 1-1/8  | 1-3/8  |

### Reducing Union Tee - Configuration B

|        | Т    | Тx   |   |    |     |   |    |    |   |    |   |    |   |   |    |   |
|--------|------|------|---|----|-----|---|----|----|---|----|---|----|---|---|----|---|
| Duolok | Tube | Tube |   |    |     |   |    |    |   |    |   |    |   |   |    |   |
| Part # | ОЛ   |      | Δ | Δv | Δ.v | в | Bv | By | C | Cr | п | Dv | E | G | Gx | н |
|        |      | 0.0. | ~ | ~  | y   | D |    | Ъу | • |    |   |    |   | 0 | 0  |   |

### Reducing Union Tee - Configuration C

|          | Т    | Тх   |      |      |      |      |      |      |      |      |      |      |      |       |       |        |
|----------|------|------|------|------|------|------|------|------|------|------|------|------|------|-------|-------|--------|
| Duolok   | Tube | Tube |      |      |      |      |      |      |      |      |      |      |      |       |       |        |
| Part #   | 0.D. | O.D. | Α    | Ax   | Ay   | В    | Bx   | Ву   | С    | Сх   | D    | Dx   | Е    | G     | Gx    | Н      |
| D8RUT66  | 1/2  | 3/8  | 2.73 | 1.42 | 1.31 | 2.04 | 1.02 | 1.02 | 0.86 | 0.76 | 0.90 | 0.66 | 0.28 | 7/8   | 11/16 | 13/16  |
| D10RUT66 | 5/8  | 3/8  | 2.95 | 1.53 | 1.42 | 2.26 | 1.13 | 1.13 | 0.86 | 0.76 | 0.96 | 0.66 | 0.28 | 1     | 11/16 | 1      |
| D12RUT66 | 3/4  | 3/8  | 3.03 | 1.57 | 1.46 | 2.34 | 1.17 | 1.17 | 0.86 | 0.76 | 0.96 | 0.66 | 0.28 | 1-1/8 | 11/16 | 1-1/16 |

### Reducing Union Tee - Configuration D

|           | Т    | Тх   | Tx1  |      |      |      |      |      |      |      |      |      |      |      |      |      |      |        |       |       |        |
|-----------|------|------|------|------|------|------|------|------|------|------|------|------|------|------|------|------|------|--------|-------|-------|--------|
| Duolok    | Tube | Tube | Tube |      |      |      |      |      |      | By   |      |      |      |      |      |      |      |        |       |       |        |
| Part #    | 0.D. | O.D. | O.D. | Α    | Ax   | Ay   | Ay1  | в    | Bx   | By1  | С    | Сх   | Cx1  | D    | Dx   | Dx1  | Е    | G      | Gx    | Gx1   | н      |
| D10RUT86  | 5/8  | 1/2  | 3/8  | 3.06 | 1.53 | 1.53 | 1.42 | 2.26 | 1.13 | 1.13 | 0.86 | 0.86 | 0.76 | 0.96 | 0.90 | 0.66 | 0.28 | 1      | 7/8   | 11/16 | 1      |
| D12RUT86  | 3/4  | 1/2  | 3/8  | 3.14 | 1.57 | 1.57 | 1.46 | 2.34 | 1.17 | 1.17 | 0.86 | 0.86 | 0.76 | 0.96 | 0.90 | 0.66 | 0.28 | 1-1/16 | 7/8   | 11/16 | 1-1/16 |
| D16RUT126 | 1    | 3/4  | 3/8  | 3.69 | 1.93 | 1.76 | 1.66 | 2.81 | 1.45 | 1.36 | 1.04 | 0.86 | 0.76 | 1.33 | 0.96 | 0.66 | 0.28 | 1-3/8  | 1-1/8 | 11/16 | 1-3/8  |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

![](_page_28_Picture_1.jpeg)

![](_page_28_Figure_2.jpeg)

### **Dielectric Adapter**

The SSP Instrumentation Dielectric Adapter is supplied with pre-swaged 3/8" nut and ferrules. The dielectric connection has a captive 1/2" nut. Dielectric Stop Collar and assembly instructions are also supplied with the adapter. By using 3/8" and 1/2" tube-ended SSP Instrumentation tube fittings with the adapter, a wide range of dielectric fitting configurations can be built.

| Duolok | T1       | T2       |      |      | G1    | G2  |
|--------|----------|----------|------|------|-------|-----|
| Part # | Tube End | Tube End | L    | Е    | Hex   | Hex |
| D8DA6  | 3/8      | 1/2      | 2.08 | 0.30 | 11/16 | 7/8 |

![](_page_28_Picture_6.jpeg)

### **Dielectric Union**

Dielectric fittings are designed to isolate monitoring and control instruments and equipment from electrical current and voltages. Manufactured in 316 stainless steel with thermoplastic insulators, SSP Instrumentation's dielectric fittings provide high dielectric strength in applications up to 5,000 PSIG. Typical applications for dielectric fittings are on impulse lines in natural gas pipeline monitoring stations. For additional factory assembled configurations, contact your local distributor.

| Duolok<br>Part # | L<br>(inches) |
|------------------|---------------|
| D4DU             | 4.08          |
| D6DU             | 4.20          |
| D8DU             | 4.79          |
| D6DMC4           | 3.80          |

# Materials and Technical DataBody: 316 Stainless SteelInsulator: Polyamide-imidePressure Rating: 5,000 PSIGTemperature Rating: From -40°F to +200°FElectrical Resistance: 1.0 x 10E7 Ohm at 70°F (20°C) at 10 VDC @ 50% relativehumidity; voltage breakdown resistance of 3,000 VDC.

## **Tube to Welded Systems**

![](_page_29_Picture_1.jpeg)

![](_page_29_Figure_2.jpeg)

### Tube Socket Weld Union

|           | Т    |      |      |      |      | E       |      |      |       |        |      |
|-----------|------|------|------|------|------|---------|------|------|-------|--------|------|
| Duolok    | Tube |      |      |      |      | Minimum |      |      |       |        |      |
| Part #    | O.D. | Α    | В    | С    | D    | Opening | F    | Fx   | G     | Н      | S    |
| D2TSWU2   | 1/8  | 1.14 | 0.88 | 0.60 | 0.50 | 0.09    | 0.34 | 0.25 | 7/16  | 7/16   | 0.31 |
| D4TSWU4   | 1/4  | 1.32 | 1.03 | 0.70 | 0.60 | 0.19    | 0.41 | 0.31 | 9/16  | 1/2    | 0.44 |
| D6TSWU6   | 3/8  | 1.48 | 1.19 | 0.76 | 0.66 | 0.28    | 0.47 | 0.38 | 11/16 | 5/8    | 0.62 |
| D8TSWU8   | 1/2  | 1.62 | 1.22 | 0.86 | 0.90 | 0.41    | 0.47 | 0.50 | 7/8   | 13/16  | 0.75 |
| D12TSWU12 | 3/4  | 1.71 | 1.31 | 0.86 | 0.96 | 0.62    | 0.47 | 0.56 | 1-1/8 | 1-1/16 | 1.05 |
| D16TSWU16 | 1    | 2.07 | 1.59 | 1.04 | 1.23 | 0.88    | 0.56 | 0.75 | 1-1/2 | 1-3/8  | 1.31 |

![](_page_29_Picture_5.jpeg)

![](_page_29_Figure_6.jpeg)

### Tube Socket Weld Elbow

| Duolok  | T<br>Tube |      |      |      |      |      | E<br>Minimum | -    |       |       |      |
|---------|-----------|------|------|------|------|------|--------------|------|-------|-------|------|
| Part #  | O.D.      | A    | BX   | Ву   | C    | D    | Opening      | Fx   | G     | н     | w    |
| D4TSWE4 | 1/4       | 1.06 | 0.77 | 0.77 | 0.70 | 0.60 | 0.19         | 0.31 | 9/16  | 1/2   | 0.50 |
| D6TSWE6 | 3/8       | 1.20 | 0.91 | 0.91 | 0.76 | 0.66 | 0.28         | 0.38 | 11/16 | 11/16 | 0.62 |
| D8TSWE8 | 1/2       | 1.42 | 1.02 | 1.02 | 0.86 | 0.90 | 0.41         | 0.50 | 7/8   | 7/8   | 0.81 |

Duolok tube fittings with weld ends allow weld system connection to tubing with the advantage of a leak tight seal that can be disassembled in an otherwise permanently welded system. Weld ends conform to ANSI B31.1 and B31.3 piping codes. **Welding precautions:** Prior to welding, remove the nut and ferrules. To protect the fitting body threads and seat, cover with a plug or another nut. Position a suitable heat sink to dissipate the heat. Insert the tube until bottomed in the socket, then back out approximately 1/16" before welding.

**Note:** The welding of a bottomed tube may lead to stress-cracking of the weld. To hold the fitting in proper alignment, tack weld the fitting in four places (90° apart) and then complete the weld. After welding, remove the protective plug or nut and replace with the nut and ferrules for tube installation following the instructions from page 9.

## **Tube to Welded Systems**

![](_page_30_Picture_1.jpeg)

![](_page_30_Figure_2.jpeg)

### Male Pipe Weld Connector

|           | Т     | Male      |      |      |      |      | E       |      |       |        |       |
|-----------|-------|-----------|------|------|------|------|---------|------|-------|--------|-------|
| Duolok    | Tube  | Pipe Weld |      |      |      |      | Minimum |      |       |        |       |
| Part #    | O.D.  | Size      | Α    | В    | С    | D    | Opening | F    | G     | н      | S     |
| D2MPWC2   | 1/8   | 1/8       | 1.20 | 0.94 | 0.60 | 0.50 | 0.09    | 0.38 | 7/16  | 7/16   | 0.405 |
| D3MPWC2   | 3/16  | 1/8       | 1.23 | 0.97 | 0.63 | 0.54 | 0.12    | 0.38 | 1/2   | 7/16   | 0.405 |
| D4MPWC2   | 1/4   | 1/8       | 1.29 | 1.00 | 0.70 | 0.60 | 0.19    | 0.38 | 9/16  | 1/2    | 0.405 |
| D4MPWC4   | 1/4   | 1/4       | 1.49 | 1.20 | 0.70 | 0.60 | 0.19    | 0.56 | 9/16  | 9/16   | 0.540 |
| D5MPWC2   | 5/16  | 1/8       | 1.34 | 1.05 | 0.73 | 0.64 | 0.20    | 0.38 | 5/8   | 9/16   | 0.405 |
| D5MPWC4   | 5/16  | 1/4       | 1.52 | 1.23 | 0.73 | 0.64 | 0.25    | 0.56 | 5/8   | 9/16   | 0.540 |
| D6MPWC4   | 3/8   | 1/4       | 1.57 | 1.28 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 5/8    | 0.540 |
| D6MPWC6   | 3/8   | 3/8       | 1.57 | 1.28 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 11/16  | 0.675 |
| D6MPWC8   | 3/8   | 1/2       | 1.82 | 1.53 | 0.76 | 0.66 | 0.28    | 0.75 | 11/16 | 7/8    | 0.840 |
| D8MPWC6   | 1/2   | 3/8       | 1.71 | 1.31 | 0.86 | 0.90 | 0.41    | 0.56 | 7/8   | 13/16  | 0.675 |
| D8MPWC8   | 1/2   | 1/2       | 1.93 | 1.53 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 7/8    | 0.840 |
| D8MPWC12  | 1/2   | 3/4       | 1.99 | 1.59 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 1-1/16 | 1.050 |
| D10MPWC8  | 5/8   | 1/2       | 1.93 | 1.53 | 0.86 | 0.96 | 0.50    | 0.75 | 1     | 15/16  | 0.840 |
| D12MPWC12 | 3/4   | 3/4       | 1.99 | 1.59 | 0.86 | 0.96 | 0.62    | 0.75 | 1-1/8 | 1-1/16 | 1.050 |
| D16MPWC16 | 1     | 1         | 2.45 | 1.97 | 1.04 | 1.23 | 0.86    | 0.94 | 1-1/2 | 1-3/8  | 1.315 |
| D20MPWC20 | 1-1/4 | 1-1/4     | 3.04 | 2.17 | 1.53 | 1.62 | 1.09    | 0.94 | 2     | 1-3/4  | 1.660 |
| D24MPWC24 | 1-1/2 | 1-1/2     | 3.50 | 2.43 | 1.78 | 1.97 | 1.34    | 1.03 | 2-1/4 | 2-1/8  | 1.900 |

![](_page_30_Picture_5.jpeg)

![](_page_30_Figure_6.jpeg)

### Male Pipe Weld Elbow

|           | Т    | Male      |      |      |      |      |      | Е       |      |       |        |       |
|-----------|------|-----------|------|------|------|------|------|---------|------|-------|--------|-------|
| Duolok    | Tube | Pipe Weld |      |      |      |      |      | Minimum |      |       |        |       |
| Part #    | O.D. | Size      | Α    | Вx   | Ву   | С    | D    | Opening | F    | G     | н      | S     |
| D4MPWE2   | 1/4  | 1/8       | 1.06 | 0.77 | 0.74 | 0.70 | 0.60 | 0.19    | 0.38 | 9/16  | 1/2    | 0.405 |
| D4MPWE4   | 1/4  | 1/4       | 1.06 | 0.77 | 0.92 | 0.70 | 0.60 | 0.19    | 0.56 | 9/16  | 1/2    | 0.540 |
| D6MPWE4   | 3/8  | 1/4       | 1.20 | 0.91 | 1.00 | 0.76 | 0.66 | 0.28    | 0.56 | 11/16 | 5/8    | 0.540 |
| D8MPWE8   | 1/2  | 1/2       | 1.42 | 1.02 | 1.30 | 0.86 | 0.90 | 0.41    | 0.75 | 7/8   | 7/8    | 0.840 |
| D12MPWE12 | 3/4  | 3/4       | 1.57 | 1.17 | 1.45 | 0.86 | 0.96 | 0.62    | 0.75 | 1-1/8 | 1-1/16 | 1.050 |

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

![](_page_31_Picture_1.jpeg)

![](_page_31_Figure_2.jpeg)

### Bulkhead Reducer/Adapter

|        | Т    |      |      |      |      |      | E       |      |       |       | Maximum   | Panel      |
|--------|------|------|------|------|------|------|---------|------|-------|-------|-----------|------------|
| Duolok | lube |      |      |      |      |      | Minimum |      |       |       | Panel     | Hole Drill |
| Part # | O.D. | Α    | Ax   | В    | Bx   | D    | Opening | F    | G     | н     | Thickness | Size       |
| D2BR2  | 1/8  | 1.95 | 1.23 | 1.69 | 0.97 | 0.50 | 0.06    | 0.53 | 7/16  | 1/2   | 0.50      | 21/64      |
| D4BR4  | 1/4  | 2.20 | 1.32 | 1.91 | 1.03 | 0.60 | 0.11    | 0.62 | 9/16  | 5/8   | 0.40      | 29/64      |
| D6BR6  | 3/8  | 2.41 | 1.45 | 2.12 | 1.16 | 0.66 | 0.24    | 0.69 | 11/16 | 3/4   | 0.44      | 37/64      |
| D8BR8  | 1/2  | 2.87 | 1.65 | 2.47 | 1.25 | 0.90 | 0.33    | 0.91 | 7/8   | 15/16 | 0.50      | 49/64      |

![](_page_31_Figure_5.jpeg)

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

![](_page_32_Picture_1.jpeg)

![](_page_32_Figure_2.jpeg)

### Reducer/Adapter\*

|        | Т     |       |      |      |      |      | E       |       |        |
|--------|-------|-------|------|------|------|------|---------|-------|--------|
| Duolok | Tube  | Тх    |      |      |      |      | Minimum |       |        |
| Part # | O.D.  | O.D.  | Α    | в    | С    | D    | Opening | G     | н      |
| D1R2   | 1/16  | 1/8   | 1.15 | 1.00 | 0.43 | 0.34 | 0.06    | 5/16  | 5/16   |
| D1R4   | 1/16  | 1/4   | 1.24 | 1.09 | 0.43 | 0.34 | 0.11    | 5/16  | 5/16   |
| D2R1   | 1/8   | 1/16  | 1.14 | 0.88 | 0.60 | 0.50 | 0.02    | 7/16  | 7/16   |
| D2R2   | 1/8   | 1/8   | 1.32 | 1.06 | 0.60 | 0.50 | 0.06    | 7/16  | 7/16   |
| D2R3   | 1/8   | 3/16  | 1.35 | 1.09 | 0.60 | 0.50 | 0.08    | 7/16  | 7/16   |
| D2R4   | 1/8   | 1/4   | 1.42 | 1.16 | 0.60 | 0.50 | 0.11    | 7/16  | 7/16   |
| D2R6   | 1/8   | 3/8   | 1.48 | 1.22 | 0.60 | 0.50 | 0.24    | 7/16  | 7/16   |
| D2R8   | 1/8   | 1/2   | 1.74 | 1.48 | 0.60 | 0.50 | 0.33    | 7/16  | 9/16   |
| D3R2   | 3/16  | 1/8   | 1.37 | 1.11 | 0.63 | 0.54 | 0.06    | 1/2   | 7/16   |
| D3R4   | 3/16  | 1/4   | 1.46 | 1.20 | 0.63 | 0.54 | 0.11    | 1/2   | 7/16   |
| D4R2   | 1/4   | 1/8   | 1.45 | 1.16 | 0.70 | 0.60 | 0.06    | 9/16  | 1/2    |
| D4R3   | 1/4   | 3/16  | 1.48 | 1.19 | 0.70 | 0.60 | 0.08    | 9/16  | 1/2    |
| D4R4   | 1/4   | 1/4   | 1.54 | 1.25 | 0.70 | 0.60 | 0.11    | 9/16  | 1/2    |
| D4R5   | 1/4   | 5/16  | 1.57 | 1.28 | 0.70 | 0.60 | 0.18    | 9/16  | 1/2    |
| D4R6   | 1/4   | 3/8   | 1.60 | 1.31 | 0.70 | 0.60 | 0.24    | 9/16  | 1/2    |
| D4R8   | 1/4   | 1/2   | 1.82 | 1.53 | 0.70 | 0.60 | 0.33    | 9/16  | 9/16   |
| D4R10  | 1/4   | 5/8   | 1.89 | 1.60 | 0.70 | 0.60 | 0.42    | 9/16  | 11/16  |
| D4R12  | 1/4   | 3/4   | 1.88 | 1.59 | 0.70 | 0.60 | 0.51    | 9/16  | 13/16  |
| D5R6   | 5/16  | 3/8   | 1.65 | 1.36 | 0.73 | 0.64 | 0.24    | 5/8   | 9/16   |
| D5R8   | 5/16  | 1/2   | 1.87 | 1.58 | 0.73 | 0.64 | 0.33    | 5/8   | 9/16   |
| D6R4   | 3/8   | 1/4   | 1.63 | 1.34 | 0.76 | 0.66 | 0.15    | 11/16 | 5/8    |
| D6R6   | 3/8   | 3/8   | 1.70 | 1.41 | 0.76 | 0.66 | 0.24    | 11/16 | 5/8    |
| D6R8   | 3/8   | 1/2   | 1.91 | 1.62 | 0.76 | 0.66 | 0.33    | 11/16 | 5/8    |
| D6R10  | 3/8   | 5/8   | 1.98 | 1.69 | 0.76 | 0.66 | 0.42    | 11/16 | 11/16  |
| D6R12  | 3/8   | 3/4   | 1.98 | 1.69 | 0.76 | 0.66 | 0.51    | 11/16 | 13/16  |
| D8R4   | 1/2   | 1/4   | 1.77 | 1.37 | 0.86 | 0.90 | 0.15    | 7/8   | 13/16  |
| D8R6   | 1/2   | 3/8   | 1.84 | 1.44 | 0.86 | 0.90 | 0.24    | 7/8   | 13/16  |
| D8R8   | 1/2   | 1/2   | 2.06 | 1.66 | 0.86 | 0.90 | 0.33    | 7/8   | 13/16  |
| D8R10  | 1/2   | 5/8   | 2.12 | 1.72 | 0.86 | 0.90 | 0.42    | 7/8   | 13/16  |
| D8R12  | 1/2   | 3/4   | 2.12 | 1.72 | 0.86 | 0.90 | 0.51    | 7/8   | 13/16  |
| D8R16  | 1/2   | 1     | 2.37 | 1.97 | 0.86 | 0.90 | 0.75    | 7/8   | 1-1/16 |
| D10R12 | 5/8   | 3/4   | 2.15 | 1.75 | 0.86 | 0.96 | 0.51    | 1     | 15/16  |
| D10R14 | 5/8   | 7/8   | 2.21 | 1.81 | 0.86 | 0.96 | 0.64    | 1     | 15/16  |
| D10R16 | 5/8   | 1     | 2.40 | 2.00 | 0.86 | 0.96 | 0.75    | 1     | 1-1/16 |
| D12R8  | 3/4   | 1/2   | 2.15 | 1.75 | 0.86 | 0.96 | 0.34    | 1-1/8 | 1-1/16 |
| D12R16 | 3/4   | 1     | 2.46 | 2.06 | 0.86 | 0.96 | 0.75    | 1-1/8 | 1-1/16 |
| D20R24 | 1-1/4 | 1-1/2 | 4.10 | 3.23 | 1.53 | 1.62 | 1.09    | 2-1/4 | 1-7/8  |

\* Note: For Heat Exchanger Tee applications (see page 27), certain Reducer/Adapter fittings can be "bored through" to accommodate a process tube's insertion. Consult with the local distributor for further information on "bored through" Reducer/Adapter (RBT) fittings.

![](_page_33_Picture_1.jpeg)

![](_page_33_Figure_2.jpeg)

### Male Adapter

|         | т    | P-NPT     |      | E       |      |        |
|---------|------|-----------|------|---------|------|--------|
| Duolok  | Tube | Male Pipe |      | Minimum | F    |        |
| Part #  | O.D. | Size      | в    | Opening | Min. | н      |
| D2MA2   | 1/8  | 1/8       | 1.12 | 0.04    | 0.38 | 7/16   |
| D2MA4   | 1/8  | 1/4       | 1.31 | 0.05    | 0.56 | 9/16   |
| D3MA2   | 3/16 | 1/8       | 1.15 | 0.08    | 0.38 | 7/16   |
| D3MA4   | 3/16 | 1/4       | 1.34 | 0.10    | 0.56 | 9/16   |
| D4MA2   | 1/4  | 1/8       | 1.21 | 0.12    | 0.38 | 7/16   |
| D4MA4   | 1/4  | 1/4       | 1.40 | 0.13    | 0.56 | 9/16   |
| D4MA6   | 1/4  | 3/8       | 1.43 | 0.14    | 0.56 | 11/16  |
| D4MA8   | 1/4  | 1/2       | 1.65 | 0.14    | 0.75 | 7/8    |
| D5MA2   | 5/16 | 1/8       | 1.25 | 0.18    | 0.38 | 7/16   |
| D5MA4   | 5/16 | 1/4       | 1.46 | 0.18    | 0.56 | 9/16   |
| D6MA2   | 3/8  | 1/8       | 1.31 | 0.19    | 0.38 | 7/16   |
| D6MA4   | 3/8  | 1/4       | 1.50 | 0.24    | 0.56 | 9/16   |
| D6MA6   | 3/8  | 3/8       | 1.50 | 0.24    | 0.56 | 11/16  |
| D6MA8   | 3/8  | 1/2       | 1.71 | 0.24    | 0.75 | 7/8    |
| D8MA4   | 1/2  | 1/4       | 1.71 | 0.28    | 0.56 | 9/16   |
| D8MA6   | 1/2  | 3/8       | 1.75 | 0.33    | 0.56 | 11/16  |
| D8MA8   | 1/2  | 1/2       | 1.93 | 0.33    | 0.75 | 7/8    |
| D10MA8  | 5/8  | 1/2       | 2.00 | 0.42    | 0.75 | 7/8    |
| D12MA8  | 3/4  | 1/2       | 2.00 | 0.47    | 0.75 | 7/8    |
| D12MA12 | 3/4  | 3/4       | 2.03 | 0.51    | 0.75 | 1-1/16 |
| D16MA12 | 1    | 3/4       | 2.28 | 0.62    | 0.75 | 1-1/16 |
| D16MA16 | 1    | 1         | 2.56 | 0.75    | 0.94 | 1-3/8  |

![](_page_33_Figure_5.jpeg)

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

![](_page_34_Picture_1.jpeg)

![](_page_34_Figure_2.jpeg)

### Female Adapter

|         | Т    | P-NPT       |      | E       |      |        |
|---------|------|-------------|------|---------|------|--------|
| Duolok  | Tube | Female Pipe |      | Minimum |      |        |
| Part #  | O.D. | Size        | В    | Opening | F    | н      |
| D2FA2   | 1/8  | 1/8         | 1.23 | 0.07    | 0.41 | 9/16   |
| D2FA4   | 1/8  | 1/4         | 1.34 | 0.07    | 0.59 | 3/4    |
| D3FA4   | 3/16 | 1/4         | 1.37 | 0.12    | 0.59 | 3/4    |
| D4FA2   | 1/4  | 1/8         | 1.32 | 0.18    | 0.41 | 9/16   |
| D4FA4   | 1/4  | 1/4         | 1.43 | 0.18    | 0.59 | 3/4    |
| D4FA6   | 1/4  | 3/8         | 1.56 | 0.18    | 0.59 | 7/8    |
| D4FA8   | 1/4  | 1/2         | 1.46 | 0.18    | 0.78 | 1-1/16 |
| D5FA4   | 5/16 | 1/4         | 1.46 | 0.25    | 0.59 | 3/4    |
| D6FA2   | 3/8  | 1/8         | 1.39 | 0.28    | 0.41 | 9/16   |
| D6FA4   | 3/8  | 1/4         | 1.50 | 0.28    | 0.59 | 3/4    |
| D6FA6   | 3/8  | 3/8         | 1.62 | 0.28    | 0.59 | 7/8    |
| D6FA8   | 3/8  | 1/2         | 1.84 | 0.28    | 0.78 | 1-1/16 |
| D8FA4   | 1/2  | 1/4         | 1.71 | 0.39    | 0.59 | 3/4    |
| D8FA6   | 1/2  | 3/8         | 1.84 | 0.39    | 0.59 | 7/8    |
| D8FA8   | 1/2  | 1/2         | 2.06 | 0.39    | 0.78 | 1-1/16 |
| D10FA8  | 5/8  | 1/2         | 2.12 | 0.50    | 0.78 | 1-1/16 |
| D12FA8  | 3/4  | 1/2         | 2.12 | 0.59    | 0.78 | 1-1/16 |
| D12FA12 | 3/4  | 3/4         | 2.18 | 0.59    | 0.81 | 1-5/16 |
| D12FA16 | 3/4  | 1           | 2.46 | 0.59    | 1.00 | 1-5/8  |
| D16FA12 | 1    | 3/4         | 2.43 | 0.95    | 0.81 | 1-1/4  |
| D16FA16 | 1    | 1           | 2.71 | 0.95    | 1.00 | 1-5/8  |

![](_page_34_Figure_5.jpeg)

![](_page_35_Picture_1.jpeg)

![](_page_35_Figure_2.jpeg)

### Port Connector

|        | т    |      | E       |      |      |
|--------|------|------|---------|------|------|
| Duolok | Tube |      | Minimum |      |      |
| Part # | O.D. | В    | Opening | F    | V    |
| D1PC   | 1/16 | 0.54 | 0.02    | 0.42 | 0.13 |
| D2PC   | 1/8  | 0.88 | 0.06    | 0.62 | 0.24 |
| D4PC   | 1/4  | 0.97 | 0.11    | 0.74 | 0.37 |
| D5PC   | 5/16 | 1.02 | 0.18    | 0.79 | 0.43 |
| D6PC   | 3/8  | 1.03 | 0.24    | 0.80 | 0.50 |
| D8PC   | 1/2  | 1.41 | 0.33    | 1.02 | 0.62 |
| D12PC  | 3/4  | 1.47 | 0.51    | 1.09 | 0.87 |
| D16PC  | 1    | 1.89 | 0.75    | 1.36 | 1.12 |

### **Reducing Port Connector**

| Duolok  | T<br>Tube | Tx<br>Reduced | Р    | E<br>Minimum | F        | E.v. | N    |
|---------|-----------|---------------|------|--------------|----------|------|------|
| Part #  | U.D.      | Tube O.D.     | Б    | Opening      | <b>F</b> | FX   | v    |
| D2RPC1  | 1/8       | 1/16          | 0.68 | 0.02         | 0.34     | 0.08 | 0.24 |
| D4RPC1  | 1/4       | 1/16          | 0.71 | 0.02         | 0.34     | 0.14 | 0.37 |
| D4RPC2  | 1/4       | 1/8           | 0.89 | 0.06         | 0.53     | 0.13 | 0.37 |
| D6RPC2  | 3/8       | 1/8           | 0.91 | 0.08         | 0.53     | 0.15 | 0.50 |
| D6RPC4  | 3/8       | 1/4           | 0.98 | 0.15         | 0.62     | 0.13 | 0.50 |
| D8RPC4  | 1/2       | 1/4           | 1.15 | 0.15         | 0.62     | 0.15 | 0.62 |
| D8RPC6  | 1/2       | 3/8           | 1.20 | 0.24         | 0.69     | 0.13 | 0.62 |
| D12RPC8 | 3/4       | 1/2           | 1.44 | 0.34         | 0.91     | 0.15 | 0.87 |

### Port connectors are used to close connect two Duolok tube fitting ports.

![](_page_35_Figure_8.jpeg)

## Installation Instructions for Port Connectors

1A. Remove the Duolok nut and ferrules from the first of the Duolok tube fitting parts to be close connected.

1B. Slide the Duolok nut (no ferrules) over the machined ferrule end of the port connector.

1C. Insert the machined ferrule end of the port connector into the Duolok tube fitting port and hand tighten the Duolok nut.

1D. While holding the tube fitting body steady with a back up wrench, tighten the Duolok nut with a wrench 1/4 turn.

2. Insert opposite end of the port connector into the second tube fitting port, hand tighten the Duolok nut, and while holding the tube fitting body steady with a back up wrench; wrench tighten the Duolok nut 1-1/4 turns for sizes 1/4" -1" and 3/4 turn for sizes 1/16" - 3/16".

| НВА |        |     |  |
|-----|--------|-----|--|
|     | puoros | SSP |  |

![](_page_36_Figure_2.jpeg)

### Hose Barb Adapter

|          |      | т    |      |      |      |      |      | F     |      |
|----------|------|------|------|------|------|------|------|-------|------|
| Duolok   | Hose | Tube |      |      | D    |      |      | Hex   |      |
| Part #   | I.D. | Size | Α    | В    | Dia. | Е    | E1   | Flat  | L    |
| D2HBA2   | 1/8  | 1/8  | 1.35 | 0.53 | 0.15 | 0.08 | 0.09 | 5/16  | .40  |
| D2HBA4   | 1/8  | 1/4  | 1.44 | 0.62 | 0.15 | 0.08 | 0.19 | 3/8   | .40  |
| D4HBA4   | 1/4  | 1/4  | 1.83 | 0.62 | 0.30 | 0.19 | 0.19 | 7/16  | .79  |
| D4HBA6   | 1/4  | 3/8  | 1.90 | 0.70 | 0.30 | 0.19 | 0.28 | 7/16  | .79  |
| D5HBA4   | 5/16 | 1/4  | 1.91 | 0.62 | 0.37 | 0.19 | 0.19 | 7/16  | .87  |
| D6HBA6   | 3/8  | 3/8  | 1.98 | 0.70 | 0.45 | 0.30 | 0.28 | 9/16  | .87  |
| D6HBA8   | 3/8  | 1/2  | 2.20 | 0.96 | 0.45 | 0.30 | 0.39 | 5/8   | .87  |
| D8HBA6   | 1/2  | 3/8  | 2.05 | 0.70 | 0.60 | 0.38 | 0.28 | 11/16 | .94  |
| D8HBA8   | 1/2  | 1/2  | 2.27 | 0.96 | 0.60 | 0.38 | 0.39 | 11/16 | .94  |
| D12HBA12 | 3/4  | 3/4  | 2.44 | 1.02 | 0.90 | 0.63 | 0.59 | 1-1/6 | 1.05 |

Heat code material traceability is available on Duolok tube fittings.

![](_page_37_Figure_1.jpeg)

![](_page_37_Figure_2.jpeg)

### **Calibration Union**

|     |       | т    |      |      |      |      | Е       |      | G    | н    |      |      |              |
|-----|-------|------|------|------|------|------|---------|------|------|------|------|------|--------------|
| Du  | lolok | Tube |      | В    |      |      | Min.    |      | Nut  | Body |      |      | R            |
| Pa  | art # | O.D. | Α    | Body | С    | D    | Opening | F    | Hex  | Hex  | I    | J    | Thread       |
| D40 | CU1   | 1/4  | 1.63 | 1.40 | 0.64 | 0.54 | 0.06    | 0.78 | 9/16 | 1/2  | 0.43 | 0.20 | 1/4 - 28 UNF |

![](_page_37_Figure_5.jpeg)

### **Calibration Union**

38

|        | т    |      |      |      |      | Е       |      |      | G    | н    |      |      |               |
|--------|------|------|------|------|------|---------|------|------|------|------|------|------|---------------|
| Duolok | Tube |      | В    |      |      | Minimum |      |      | Nut  | Body |      |      | R             |
| Part # | O.D. | Α    | Body | С    | D    | Opening | Fx   | Fy   | Hex  | Hex  | I    | J    | Thread        |
| D4CU2  | 1/4  | 2.26 | 2.03 | 0.64 | 0.54 | 0.06    | 0.41 | 1.00 | 9/16 | 1/2  | 0.40 | 0.25 | 5/16 - 24 UNF |

SSP Instrumentation Calibration Unions streamline the typical DP transmitter calibration process and are available in 1/4" OD tubing by 1/4-28 straight thread, and 1/4" OD tubing by 5/16-24 straight thread. Calibration unions screw directly into plug/bleed port fittings, eliminating the possibility of galling the transmitter's NPT threads. Standard fitting material is 316 stainless steel. For more information, contact your local distributor.

## Duolok to 37° Flare (AN)

![](_page_38_Picture_1.jpeg)

![](_page_38_Figure_2.jpeg)

### AN Union

|          | Т    | AN         |      |      |      |      | E       |       |       |                   |
|----------|------|------------|------|------|------|------|---------|-------|-------|-------------------|
| Duolok   | Tube | Tube       |      |      |      |      | Minimum |       |       |                   |
| Part #   | O.D. | Flare Size | Α    | В    | С    | D    | Opening | G     | Н     | R                 |
| D1ANU2   | 1/16 | 1/8        | 1.07 | 0.92 | 0.43 | 0.34 | 0.05    | 5/16  | 7/16  | 5/16 - 24 UNJF-3  |
| D2ANU2   | 1/8  | 1/8        | 1.27 | 1.01 | 0.60 | 0.50 | 0.06    | 7/16  | 7/16  | 5/16 - 24 UNJF-3  |
| D2ANU4   | 1/8  | 1/4        | 1.38 | 1.12 | 0.60 | 0.50 | 0.09    | 7/16  | 1/2   | 7/16 - 20 UNJF-3  |
| D4ANU4   | 1/4  | 1/4        | 1.48 | 1.19 | 0.70 | 0.60 | 0.17    | 9/16  | 1/2   | 7/16 - 20 UNJF-3  |
| D5ANU5   | 5/16 | 5/16       | 1.51 | 1.22 | 0.73 | 0.64 | 0.23    | 5/8   | 9/16  | 1/2 - 20 UNJF-3   |
| D6ANU4   | 3/8  | 1/4        | 1.56 | 1.27 | 0.76 | 0.66 | 0.17    | 11/16 | 5/8   | 7/16 - 20 UNJF-3  |
| D6ANU6   | 3/8  | 3/8        | 1.56 | 1.27 | 0.76 | 0.66 | 0.28    | 11/16 | 5/8   | 9/16 - 18 UNJF-3  |
| D8ANU8   | 1/2  | 1/2        | 1.81 | 1.41 | 0.86 | 0.90 | 0.39    | 7/8   | 13/16 | 3/4 - 16 UNJF-3   |
| D12ANU12 | 3/4  | 3/4        | 2.10 | 1.70 | 0.86 | 0.96 | 0.61    | 1-1/8 | 1-1/8 | 1-1/16 - 12 UNJ-3 |
| D16ANU16 | 1    | 1          | 2.42 | 1.94 | 1.04 | 1.23 | 0.84    | 1-1/2 | 1-3/8 | 1-5/16 - 12 UNJ-3 |

![](_page_38_Picture_5.jpeg)

![](_page_38_Figure_6.jpeg)

### AN Bulkhead Union

|           | т    | AN         |      |      |      |      |      | Е       |       |        |                   | Maximum   | Panel      |
|-----------|------|------------|------|------|------|------|------|---------|-------|--------|-------------------|-----------|------------|
| Duolok    | Tube | Tube       |      |      |      |      |      | Minimum |       |        |                   | Panel     | Hole Drill |
| Part #    | O.D. | Flare Size | Α    | Ах   | В    | Вx   | D    | Opening | G     | н      | R                 | Thickness | Size       |
| D4ANBU4   | 1/4  | 1/4        | 2.12 | 1.32 | 1.83 | 1.03 | 0.60 | 0.17    | 9/16  | 5/8    | 7/16 - 20 UNJF-3  | 0.40      | 29/64      |
| D6ANBU6   | 3/8  | 3/8        | 2.25 | 1.45 | 1.96 | 1.16 | 0.66 | 0.28    | 11/16 | 3/4    | 9/16 - 18 UNJF-3  | 0.44      | 37/64      |
| D8ANBU8   | 1/2  | 1/2        | 2.59 | 1.65 | 2.19 | 1.25 | 0.90 | 0.39    | 7/8   | 15/16  | 3/4 - 16 UNJF-3   | 0.50      | 49/64      |
| D12ANBU12 | 3/4  | 3/4        | 3.11 | 1.87 | 2.71 | 1.47 | 0.96 | 0.61    | 1-1/8 | 1-3/16 | 1-1/16 - 12 UNJ-3 | 0.66      | 1-1/64     |
| D16ANBU16 | 1    | 1          | 3.64 | 2.26 | 3.16 | 1.78 | 1.23 | 0.84    | 1-1/2 | 1-5/8  | 1-5/16 - 12 UNJ-3 | 0.75      | 1-21/64    |

*Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.* When ordering, specify material designator with part number (see page 3 for complete ordering information).

## Duolok to 37° Flare (AN)

![](_page_39_Picture_1.jpeg)

![](_page_39_Figure_2.jpeg)

### Female AN Adapter\*

|        | Т    | AN    |      |      | G     | Gx    |      | R                |
|--------|------|-------|------|------|-------|-------|------|------------------|
| Duolok | Tube | Flare |      |      | Hex   | Hex   |      | AN Thread        |
| Part # | O.D. | Size  | В    | F    | Flat  | Flat  | Ν    | Size             |
| D2ANF2 | 1/8  | 1/8   | 0.75 | 0.53 | 7/16  | 3/8   | 0.54 | 5/16 - 24 UNJF-3 |
| D2ANF4 | 1/8  | 1/4   | 0.78 | 0.53 | 7/16  | 9/16  | 0.62 | 7/16 - 20 UNJF-3 |
| D4ANF4 | 1/4  | 1/4   | 0.86 | 0.62 | 9/16  | 9/16  | 0.62 | 7/16 - 20 UNJF-3 |
| D6ANF6 | 3/8  | 3/8   | 1.02 | 0.70 | 11/16 | 11/16 | 0.72 | 9/16 - 18 UNJF-3 |
| D8ANF8 | 1/2  | 1/2   | 1.31 | 0.92 | 7/8   | 7/8   | 0.85 | 3/4 - 16 UNJF-3  |

\* Follow Reassembly Instructions from page 9 for assembly of the Duolok end of the ANF fitting.

![](_page_39_Picture_6.jpeg)

40

![](_page_39_Figure_7.jpeg)

### AN Adapter

|          | Т    | AN Tube | В      | R                 | E       | н     |
|----------|------|---------|--------|-------------------|---------|-------|
| Duolok   | Tube | Flare   | Body   | AN Thread         | Minimum | Hex   |
| Part #   | O.D. | Size    | Length | Size              | Opening | Flat  |
| D4ANA4   | 1/4  | 1/4     | 1.46   | 7/16 - 20 UNJF-3  | 0.17    | 1/2   |
| D6ANA4   | 3/8  | 1/4     | 1.53   | 7/16 - 20 UNJF-3  | 0.17    | 1/2   |
| D6ANA6   | 3/8  | 3/8     | 1.56   | 9/16 - 18 UNJF-3  | 0.26    | 5/8   |
| D8ANA8   | 1/2  | 1/2     | 1.91   | 3/4 - 16 UNJF-3   | 0.36    | 13/16 |
| D12ANA12 | 3/4  | 3/4     | 2.21   | 1-1/16 - 12 UNJ-3 | 0.59    | 1-1/8 |
| D16ANA16 | 1    | 1       | 2.58   | 1-5/16 - 12 UNJ-3 | 0.82    | 1-3/8 |

## **Tube to O-Ring Seal**

### **O-Ring Seal Connectors**

Duolok O-Ring Seal Connectors provide a leak-tight seal in vacuum or pressure systems having tapered pipe or straight thread ports and a smooth, flat seat surface perpendicular to the axis of the threads. (See Figures 1-3.) To produce an effective seal, the connectors are manufactured with a precision groove that retains the O-Ring and prevents its extrusion from the sealing area. The connectors are designed to seal upon a raised, flat surface or with a counter bored or recessed hole. The following O-Ring Seal installation instructions and mounting dimensions chart should be helpful when working with O-Ring Seal Connectors.

### **O-Ring Seal Connector Installation Instructions**

- 1. Lubricate the O-Ring with a lubricant that is compatible with the O-Ring material and the system's media and environment. (Standard O-Ring material is BUNA compound, 70 Durometer. Viton and other O-Ring compounds are available.)
- 2. Hand tighten the connector until the O-Ring begins to compress.
- 3. With a wrench, slightly snug the connector to compress the O-Ring to the port and achieve the seal.
- 4. When connecting or disconnecting tubing to the Duolok fitting end of the connector, always use a backup wrench to retain the connector's installed position.

![](_page_40_Figure_8.jpeg)

| MO      |             | NSIONS FO   | R O-RING | SEAL CON | NECTORS |         |  |  |  |  |  |
|---------|-------------|-------------|----------|----------|---------|---------|--|--|--|--|--|
|         |             | A B C D     |          |          |         |         |  |  |  |  |  |
|         |             | A           | В        | С        | D       | E       |  |  |  |  |  |
|         |             | Minimum     | Minimum  | Minimum  | Maximum | Maximum |  |  |  |  |  |
| Pipe    | Straight    | Flat        |          |          |         |         |  |  |  |  |  |
| Thread  | Thread      | Surface     |          |          |         |         |  |  |  |  |  |
| Size    | Size        | for Sealing |          |          |         |         |  |  |  |  |  |
| 1/8 NPT | —           | 0.69        | 0.78     | 0.88     | 0.16    | 0.28    |  |  |  |  |  |
| 1/4 NPT | —           | 0.87        | 0.97     | 1.09     | 0.16    | 0.31    |  |  |  |  |  |
| 3/8 NPT | —           | 1.00        | 1.16     | 1.31     | 0.16    | 0.34    |  |  |  |  |  |
| 1/2 NPT | —           | 1.00        | 1.34     | 1.53     | 0.22    | 0.44    |  |  |  |  |  |
| —       | 5/16 - 24   | 0.50        | 0.59     | 0.66     | 0.09    | 0.16    |  |  |  |  |  |
| —       | 3/8 - 24    | 0.56        | 0.66     | 0.75     | 0.09    | 0.22    |  |  |  |  |  |
| —       | 7/16 - 20   | 0.69        | 0.78     | 0.88     | 0.16    | 0.28    |  |  |  |  |  |
| —       | 1/2 - 20    | 0.75        | 0.91     | 1.03     | 0.16    | 0.31    |  |  |  |  |  |
| —       | 9/16 - 18   | 0.81        | 0.97     | 1.09     | 0.16    | 0.31    |  |  |  |  |  |
| —       | 3/4 - 16    | 1.00        | 1.16     | 1.31     | 0.16    | 0.34    |  |  |  |  |  |
| —       | 1-1/16 - 12 | 1.41        | 1.53     | 1.75     | 0.22    | 0.50    |  |  |  |  |  |
| _       | 1-5/16 - 12 | 1.69        | 1.78     | 2.03     | 0.22    | 0.56    |  |  |  |  |  |

## **Tube to O-Ring Seal**

![](_page_41_Picture_1.jpeg)

![](_page_41_Figure_2.jpeg)

### O-Ring Seal Male Connector (Connects to Female Short NPT Thread)

|        | Т    | P-NPT*    |      |      |      |      | E       |      |       |        |      | AS568 O-Ring |
|--------|------|-----------|------|------|------|------|---------|------|-------|--------|------|--------------|
| Duolok | Tube | Male Pipe |      |      |      |      | Minimum |      |       |        |      | Uniform Size |
| Part # | O.D. | Size      | Α    | В    | С    | D    | Opening | F    | G     | н      | Hd   | Number**     |
| D2OMC2 | 1/8  | 1/8       | 1.29 | 1.03 | 0.60 | 0.50 | 0.09    | 0.28 | 7/16  | 3/4    | 0.74 | -111         |
| D4OMC2 | 1/4  | 1/8       | 1.38 | 1.09 | 0.70 | 0.60 | 0.19    | 0.28 | 9/16  | 3/4    | 0.74 | -111         |
| D4OMC4 | 1/4  | 1/4       | 1.51 | 1.22 | 0.70 | 0.60 | 0.19    | 0.38 | 9/16  | 15/16  | 0.93 | -113         |
| D6OMC4 | 3/8  | 1/4       | 1.57 | 1.28 | 0.76 | 0.66 | 0.28    | 0.38 | 11/16 | 15/16  | 0.93 | -113         |
| D6OMC6 | 3/8  | 3/8       | 1.63 | 1.34 | 0.76 | 0.66 | 0.28    | 0.41 | 11/16 | 1-1/8  | 1.12 | -116         |
| D6OMC8 | 3/8  | 1/2       | 1.85 | 1.56 | 0.76 | 0.66 | 0.28    | 0.53 | 11/16 | 1-5/16 | 1.30 | -212         |
| D8OMC8 | 1/2  | 1/2       | 1.96 | 1.56 | 0.86 | 0.90 | 0.41    | 0.53 | 7/8   | 1-5/16 | 1.30 | -212         |

\* Modified Male NPT to Allow O-Ring Seal Connection
\*\* 70 Durometer BUNA compound O-Ring is standard. Other O-Ring compounds are available.

![](_page_41_Figure_7.jpeg)

![](_page_41_Figure_8.jpeg)

### O-Ring Seal Male Straight Thread Connector (Connects to Female Straight Thread)

| Duelek   | T    | S           |      |      |      |      | E       |      |       |       |      | AS568 O-Ring |
|----------|------|-------------|------|------|------|------|---------|------|-------|-------|------|--------------|
| Duolok   | Banı | Thread      |      |      |      |      | Minimum |      |       |       |      | Uniform Size |
| Part #   | O.D. | Size        | Α    | В    | С    | D    | Opening | F    | G     | н     | Hd   | Number*      |
| D1OSC2   | 1/16 | 5/16 - 24   | 1.05 | 0.90 | 0.43 | 0.34 | 0.05    | 0.34 | 5/16  | 9/16  | 0.55 | -011         |
| D2OSC2   | 1/8  | 5/16 - 24   | 1.29 | 1.03 | 0.60 | 0.50 | 0.09    | 0.34 | 7/16  | 9/16  | 0.55 | -011         |
| D3OSC3   | 3/16 | 3/8 - 24    | 1.35 | 1.09 | 0.63 | 0.54 | 0.12    | 0.38 | 1/2   | 5/8   | 0.62 | -012         |
| D4OSC4   | 1/4  | 7/16 - 20   | 1.51 | 1.22 | 0.70 | 0.60 | 0.19    | 0.41 | 9/16  | 3/4   | 0.74 | -111         |
| D5OSC5   | 5/16 | 1/2 - 20    | 1.60 | 1.31 | 0.73 | 0.64 | 0.25    | 0.44 | 5/8   | 7/8   | 0.86 | -112         |
| D6OSC6   | 3/8  | 9/16 - 18   | 1.67 | 1.38 | 0.76 | 0.66 | 0.28    | 0.47 | 11/16 | 15/16 | 0.93 | -113         |
| D8OSC8   | 1/2  | 3/4 - 16    | 1.81 | 1.41 | 0.86 | 0.90 | 0.41    | 0.47 | 7/8   | 1-1/8 | 1.12 | -116         |
| D12OSC12 | 3/4  | 1-1/16 - 12 | 2.06 | 1.66 | 0.86 | 0.96 | 0.62    | 0.56 | 1-1/8 | 1-1/2 | 1.49 | -215         |
| D16OSC16 | 1    | 1-5/16 - 12 | 2.29 | 1.81 | 1.04 | 1.23 | 0.88    | 0.56 | 1-1/2 | 1-3/4 | 1.74 | -219         |

\* 70 Durometer BUNA compound O-Ring is standard. Other O-Ring compounds are available.

![](_page_42_Picture_1.jpeg)

![](_page_42_Picture_2.jpeg)

These fittings adapt to SAE/J1926 (Straight Thread Boss) and MS16142 (Boss).

### Male Connector - Straight Thread Boss

|           | т     | S           |      |      |      |      | Е       |      |       |        | AS568 O-Ring |
|-----------|-------|-------------|------|------|------|------|---------|------|-------|--------|--------------|
| Duolok    | Tube  | Thread      |      |      |      |      | Minimum |      |       |        | Uniform Size |
| Part #    | O.D.  | Size        | Α    | В    | С    | D    | Opening | F    | G     | н      | Number*      |
| D2MCST2   | 1/8   | 5/16 - 24   | 1.18 | 0.92 | 0.60 | 0.50 | 0.09    | 0.30 | 7/16  | 7/16   | -902         |
| D4MCST4   | 1/4   | 7/16 - 20   | 1.34 | 1.05 | 0.70 | 0.60 | 0.19    | 0.36 | 9/16  | 9/16   | -904         |
| D4MCST6   | 1/4   | 9/16 - 18   | 1.40 | 1.11 | 0.70 | 0.60 | 0.19    | 0.39 | 9/16  | 11/16  | -906         |
| D4MCST8   | 1/4   | 3/4 - 16    | 1.48 | 1.19 | 0.70 | 0.60 | 0.19    | 0.44 | 9/16  | 7/8    | -908         |
| D4MCST10  | 1/4   | 7/8 - 14    | 1.60 | 1.31 | 0.70 | 0.60 | 0.19    | 0.50 | 9/16  | 1      | -910         |
| D5MCST5   | 5/16  | 1/2 - 20    | 1.37 | 1.08 | 0.73 | 0.64 | 0.25    | 0.36 | 5/8   | 5/8    | -905         |
| D6MCST4   | 3/8   | 7/16 - 20   | 1.40 | 1.11 | 0.76 | 0.66 | 0.20    | 0.36 | 11/16 | 5/8    | -904         |
| D6MCST6   | 3/8   | 9/16 - 18   | 1.46 | 1.17 | 0.76 | 0.66 | 0.28    | 0.39 | 11/16 | 11/16  | -906         |
| D6MCST8   | 3/8   | 3/4 - 16    | 1.54 | 1.25 | 0.76 | 0.66 | 0.28    | 0.44 | 11/16 | 7/8    | -908         |
| D6MCST10  | 3/8   | 7/8 - 14    | 1.66 | 1.37 | 0.76 | 0.66 | 0.28    | 0.50 | 11/16 | 1      | -910         |
| D8MCST6   | 1/2   | 9/16 - 18   | 1.54 | 1.14 | 0.86 | 0.90 | 0.28    | 0.39 | 7/8   | 13/16  | -906         |
| D8MCST8   | 1/2   | 3/4 - 16    | 1.65 | 1.25 | 0.86 | 0.90 | 0.41    | 0.44 | 7/8   | 7/8    | -908         |
| D8MCST10  | 1/2   | 7/8 - 14    | 1.77 | 1.37 | 0.86 | 0.90 | 0.41    | 0.50 | 7/8   | 1      | -910         |
| D8MCST12  | 1/2   | 1-1/16 - 12 | 1.93 | 1.53 | 0.86 | 0.90 | 0.41    | 0.59 | 7/8   | 1-1/4  | -912         |
| D10MCST8  | 5/8   | 3/4 - 16    | 1.65 | 1.25 | 0.86 | 0.96 | 0.42    | 0.44 | 1     | 15/16  | -908         |
| D10MCST10 | 5/8   | 7/8 - 14    | 1.78 | 1.38 | 0.86 | 0.96 | 0.50    | 0.50 | 1     | 1      | -910         |
| D12MCST8  | 3/4   | 3/4 - 16    | 1.81 | 1.41 | 0.86 | 0.96 | 0.42    | 0.44 | 1-1/8 | 1-1/16 | -908         |
| D12MCST12 | 3/4   | 1-1/16 - 12 | 1.93 | 1.53 | 0.86 | 0.96 | 0.62    | 0.59 | 1-7/8 | 1-1/4  | -912         |
| D14MCST14 | 7/8   | 1-3/16 - 12 | 1.93 | 1.53 | 0.86 | 1.02 | 0.72    | 0.59 | 1-1/4 | 1-3/8  | -914         |
| D16MCST12 | 1     | 1-1/16 - 12 | 2.10 | 1.62 | 1.04 | 1.23 | 0.66    | 0.59 | 1-1/2 | 1-3/8  | -912         |
| D16MCST16 | 1     | 1-5/16 - 12 | 2.14 | 1.66 | 1.04 | 1.23 | 0.88    | 0.59 | 1-1/2 | 1-1/2  | -916         |
| D20MCST20 | 1-1/4 | 1-5/16 - 12 | 2.69 | 1.82 | 1.53 | 1.62 | 1.09    | 0.59 | 1-7/8 | 1-7/8  | -920         |
| D24MCST24 | 1-1/2 | 1-7/8 - 12  | 3.06 | 1.99 | 1.78 | 1.97 | 1.34    | 0.59 | 2-1/4 | 2-1/8  | -924         |

\*90 Durometer Viton O-Ring is standard. Other O-Ring compounds are available.

![](_page_43_Picture_1.jpeg)

![](_page_43_Figure_2.jpeg)

### Male Elbow - Straight Thread Boss

| Duolok<br>Part # | T<br>Tube<br>O.D. | S<br>SAE/MS<br>Thread<br>Size | A    | с    | D    | E<br>Min.<br>Opening | H<br>Wrench<br>Pad | Hx<br>Hex<br>Flat | G<br>Hex<br>Flat | Bx   | Ву   | AS568<br>O-Ring<br>Uniform Size<br>Number* |
|------------------|-------------------|-------------------------------|------|------|------|----------------------|--------------------|-------------------|------------------|------|------|--|
| D4MEST4          | 1/4               | 7/16 - 20                     | 1.12 | 0.70 | 0.60 | 0.19                 | 1/2                | 9/16              | 9/16             | 0.83 | 1.12 | -904                                       |
| D4MEST6          | 1/4               | 9/16 - 18                     | 1.20 | 0.70 | 0.60 | 0.19                 | 5/8                | 11/16             | 9/16             | 0.91 | 1.27 | -906                                       |
| D5MEST5          | 5/16              | 1/2-20                        | 1.19 | 0.73 | 0.64 | 0.23                 | 9/16               | 5/8               | 5/8              | 0.90 | 1.16 | -905                                       |
| D6MEST4          | 3/8               | 7/16 - 20                     | 1.26 | 0.76 | 0.66 | 0.28                 | 9/16               | 9/16              | 11/16            | 0.97 | 1.15 | -904                                       |
| D6MEST6          | 3/8               | 9/16-18                       | 1.26 | 0.76 | 0.66 | 0.28                 | 9/16               | 11/16             | 11/16            | 0.97 | 1.27 | -906                                       |
| D6MEST8          | 3/8               | 3/4 - 16                      | 1.37 | 0.76 | 0.66 | 0.28                 | 3/4                | 7/8               | 11/16            | 1.08 | 1.49 | -908                                       |
| D8MEST6          | 1/2               | 9/16-18                       | 1.48 | 0.86 | 0.90 | 0.41                 | 3/4                | 11/16             | 7/8              | 1.08 | 1.27 | -906                                       |
| D8MEST8          | 1/2               | 3/4-16                        | 1.48 | 0.86 | 0.90 | 0.41                 | 13/16              | 7/8               | 7/8              | 1.08 | 1.49 | -908                                       |
| D10MEST10        | 5/8               | 7/8 - 14                      | 1.56 | 0.86 | 0.96 | 0.50                 | 15/16              | 1                 | 1                | 1.16 | 1.71 | -910                                       |
| D12MEST12        | 3/4               | 1-1/16 - 12                   | 1.63 | 0.86 | 0.96 | 0.62                 | 1-1/16             | 1-1/4             | 1-1/8            | 1.23 | 1.92 | -912                                       |
| D16MEST16        | 1                 | 1-5/16 - 12                   | 1.99 | 1.04 | 1.23 | 0.88                 | 1-3/8              | 1-1/2             | 1-1/2            | 1.51 | 2.11 | -916                                       |
| D20MEST20        | 1-1/4             | 1-5/8 - 12                    | 2.67 | 1.53 | 1.62 | 1.09                 | 1-11/16            | 1-7/8             | 1-7/8            | 1.80 | 2.29 | -920                                       |

\*90 Durometer Viton O-Ring is standard. Other O-Ring compounds are available.

![](_page_43_Picture_6.jpeg)

![](_page_43_Figure_7.jpeg)

### 45° Male Elbow - Straight Thread Boss

| Duolok<br>Port # | T<br>Tube | S<br>SAE/MS<br>Thread |      | (    | 6    | E<br>Min. | H<br>Wrench | Hx<br>Hex<br>Flat | G<br>Hex<br>Elat | Dir  | Dir  | AS568<br>O-Ring<br>Uniform Size |
|------------------|-----------|-----------------------|------|------|------|-----------|-------------|-------------------|------------------|------|------|---------------------------------|
| Part #           | U.U.      | Size                  | A    | C    | D    | Opening   | Pad         | Flat              | Flat             | BX   | Ву   | Number                          |
| D4M45EST4        | 1/4       | 7/16 - 20             | 1.01 | 0.70 | 0.60 | 0.19      | 1/2         | 9/16              | 9/16             | 0.72 | 1.01 | -904                            |
| D6M45EST6        | 3/8       | 9/16 - 18             | 1.10 | 0.76 | 0.66 | 0.28      | 5/8         | 11/16             | 11/16            | 0.81 | 1.11 | -906                            |
| D8M45EST8        | 1/2       | 3/4 - 16              | 1.26 | 0.86 | 0.90 | 0.41      | 13/16       | 7/8               | 7/8              | 0.86 | 1.27 | -908                            |
| D12M45EST12      | 3/4       | 1-1/16 - 12           | 1.57 | 0.86 | 0.96 | 0.62      | 1-1/8       | 1-1/4             | 1-1/8            | 1.17 | 1.86 | -912                            |
| D16M45EST16      | 1         | 1-5/16 - 12           | 1.87 | 1.04 | 1.23 | 0.88      | 1-3/8       | 1-1/2             | 1-1/2            | 1.39 | 1.99 | -916                            |

\*90 Durometer Viton O-Ring is standard. Other O-Ring compounds are available.

![](_page_44_Picture_1.jpeg)

![](_page_44_Figure_2.jpeg)

### Male Branch Tee - Straight Thread Boss

|            |              | S           |      |      |      |      |         |        |       |       |      |      | AS568        |
|------------|--------------|-------------|------|------|------|------|---------|--------|-------|-------|------|------|--------------|
|            | Т            | SAE/MS      |      |      |      |      | E       | н      | Hx    | G     |      |      | O-Ring       |
| Duolok     | Tube         | Thread      |      |      |      |      | Min.    | Wrench | Hex   | Hex   |      |      | Uniform Size |
| Part #     | <b>O</b> .D. | Size        | Α    | Ax   | С    | D    | Opening | Pad    | Flat  | Flat  | В    | Вx   | Number*      |
| D4MBTST4   | 1/4          | 7/16 - 20   | 2.24 | 1.12 | 0.70 | 0.60 | 0.19    | 1/2    | 9/16  | 9/16  | 1.66 | 0.83 | -904         |
| D6MBTST6   | 3/8          | 9/16 - 18   | 2.52 | 1.26 | 0.76 | 0.66 | 0.28    | 5/8    | 11/16 | 11/16 | 1.94 | 0.97 | -906         |
| D8MBTST8   | 1/2          | 3/4 - 16    | 2.96 | 1.48 | 0.86 | 0.90 | 0.41    | 13/16  | 7/8   | 7/8   | 2.16 | 1.08 | -908         |
| D12MBTST12 | 3/4          | 1-1/16 - 12 | 3.26 | 1.63 | 0.86 | 0.96 | 0.62    | 1-1/16 | 1-1/4 | 1-1/8 | 2.46 | 1.23 | -912         |
| D16MBTST16 | 1            | 1-5/16 - 12 | 3.98 | 1.99 | 1.04 | 1.23 | 0.88    | 1-3/8  | 1-1/2 | 1-1/2 | 3.02 | 1.51 | -916         |

\*90 Durometer Viton O-Ring is standard. Other O-Ring compounds are available.

![](_page_44_Figure_6.jpeg)

![](_page_44_Figure_7.jpeg)

### Male Run Tee - Straight Thread Boss

|            | т    | S<br>SAF/MS |      |      |      |      | F         | н      | Нх    | G     |      |      |      | AS568<br>O-Ring |
|------------|------|-------------|------|------|------|------|-----------|--------|-------|-------|------|------|------|-----------------|
| Duolok     | Tube | Thread      |      |      |      |      | _<br>Min. | Wrench | Hex   | Hex   |      |      |      | Uniform Size    |
| Part #     | O.D. | Size        | Α    | Ax   | С    | D    | Opening   | Pad    | Flat  | Flat  | В    | Вx   | Ву   | Number*         |
| D4MRTST4   | 1/4  | 7/16 - 20   | 2.24 | 1.12 | 0.70 | 0.60 | 0.19      | 1/2    | 9/16  | 9/16  | 1.95 | 0.83 | 1.12 | -904            |
| D6MRTST6   | 3/8  | 9/16 - 18   | 2.53 | 1.26 | 0.76 | 0.66 | 0.28      | 5/8    | 11/16 | 11/16 | 2.24 | 0.97 | 1.27 | -906            |
| D8MRTST8   | 1/2  | 3/4 - 16    | 2.97 | 1.48 | 0.86 | 0.90 | 0.41      | 13/16  | 7/8   | 7/8   | 2.57 | 1.08 | 1.49 | -908            |
| D12MRTST12 | 3/4  | 1-1/16 - 12 | 3.55 | 1.63 | 0.86 | 0.96 | 0.62      | 1-1/16 | 1-1/4 | 1-1/8 | 3.15 | 1.23 | 1.92 | -912            |
| D16MRTST16 | 1    | 1-5/16 - 12 | 4.10 | 1.99 | 1.04 | 1.23 | 0.88      | 1-3/8  | 1-1/2 | 1-1/2 | 3.62 | 1.51 | 2.11 | -916            |

\*90 Durometer Viton O-Ring is standard. Other O-Ring compounds are available.

![](_page_45_Picture_1.jpeg)

![](_page_45_Figure_2.jpeg)

### Male Adapter - Straight Thread Boss

|                  | т            | S<br>SAE/MS    |      |      | E               | н           | AS568<br>O-Ring         |
|------------------|--------------|----------------|------|------|-----------------|-------------|-------------------------|
| Duolok<br>Part # | Tube<br>O.D. | Thread<br>Size | А    | F    | Mın.<br>Opening | Hex<br>Flat | Uniform Size<br>Number* |
| D2MAST2          | 1/8          | 5/16 - 24      | 1.20 | 0.30 | 0.09            | 7/16        | -902                    |
| D4MAST4          | 1/4          | 7/16 - 20      | 1.39 | 0.36 | 0.19            | 9/16        | -904                    |
| D6MAST4          | 3/8          | 7/16 - 20      | 1.46 | 0.36 | 0.19            | 9/16        | -904                    |
| D6MAST6          | 3/8          | 9/16 - 18      | 1.52 | 0.39 | 0.28            | 11/16       | -906                    |
| D6MAST8          | 3/8          | 3/4 - 16       | 1.60 | 0.44 | 0.28            | 7/8         | -908                    |
| D8MAST6          | 1/2          | 9/16 - 18      | 1.74 | 0.39 | 0.39            | 11/16       | -906                    |
| D8MAST8          | 1/2          | 3/4 - 16       | 1.82 | 0.44 | 0.39            | 7/8         | -908                    |
| D12MAST12        | 3/4          | 1-1/16 - 12    | 2.10 | 0.59 | 0.59            | 1-1/4       | -912                    |
| D16MAST16        | 1            | 1-5/16 - 12    | 2.41 | 0.59 | 0.80            | 1-1/2       | -916                    |

\*90 Durometer Viton O-Ring is standard. Other O-Ring compounds are available.

46

## **Cap and Plug**

NUT HEX Caps are used for capping С an end of a tubing run. Cap т Duolok Tube Part # O.D. в С D G н Α D1CP 1/16 0.59 0.44 0.43 0.34 5/16 5/16 D2CP 1/8 0.79 0.53 0.60 0.50 7/16 7/16 D3CP 3/16 0.58 0.54 7/16 0.84 0.63 1/2 D4CP 0.92 0.63 0.70 0.60 9/16 1/2 1/4 D5CP 5/16 0.96 0.67 0.73 0.64 5/8 9/16 page 9). D6CP 3/8 1.01 0.72 0.76 0.66 11/16 5/8 D8CP 1/2 1.15 0.75 0.86 0.90 7/8 13/16 D10CP 0.78 5/8 1.18 0.86 0.96 15/16 1 D12CP 3/4 1.24 0.84 0.86 0.96 1-1/8 1-1/16 D14CP 7/8 1.34 0.94 0.86 1.02 1-1/4 1-3/16

![](_page_46_Figure_2.jpeg)

### **Cap Installation Instructions** The standard Duolok tube fitting installation instructions apply for proper installation of caps (see

![](_page_46_Figure_4.jpeg)

![](_page_46_Picture_5.jpeg)

D16CP

D20CP

D24CP

Ρ

1

1-1/4

1-1/2

1.51

2.10

2.54

1.03

1.23

1.47

1.04

1.53

1.78

1.23

1.62

1.97

1 - 1/2

1-7/8

2-1/4

1-3/8

1-3/4

2-1/8

![](_page_46_Picture_6.jpeg)

Plugs are used to plug an unused port of a Duolok tube fitting.

### Plug

|        | т     |       |  |
|--------|-------|-------|--|
| Duolok | Tube  |       |  |
| Part # | O.D.  | G     |  |
| D1P    | 1/16  | 5/16  |  |
| D2P    | 1/8   | 7/16  |  |
| D3P    | 3/16  | 1/2   |  |
| D4P    | 1/4   | 9/16  |  |
| D5P    | 5/16  | 5/8   |  |
| D6P    | 3/8   | 11/16 |  |
| D8P    | 1/2   | 7/8   |  |
| D10P   | 5/8   | 1     |  |
| D12P   | 3/4   | 1-1/8 |  |
| D16P   | 1     | 1-1/2 |  |
| D20P   | 1-1/4 | 1-7/8 |  |
| D24P   | 1-1/2 | 2-1/4 |  |

### **Plug Installation Instructions**

1. Remove the nut and ferrules from the port of the tube fitting body to be plugged and replace with the Duolok plug.

2. Hand-tighten the Duolok plug and then while holding the tube fitting body steady with a back-up wrench, use a wrench to tighten the Duolok plug only 1/4 of a turn.

![](_page_46_Picture_13.jpeg)

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change. When ordering, specify material designator with part number (see page 3 for complete ordering information).

## Components

![](_page_47_Picture_1.jpeg)

| Nut    |       |       |      |
|--------|-------|-------|------|
|        | Т     |       |      |
| Duolok | Tube  |       |      |
| Part # | O.D.  | G     | L    |
| D1N    | 1/16  | 5/16  | 0.31 |
| D2N    | 1/8   | 7/16  | 0.47 |
| D3N    | 3/16  | 1/2   | 0.47 |
| D4N    | 1/4   | 9/16  | 0.50 |
| D5N    | 5/16  | 5/8   | 0.53 |
| D6N    | 3/8   | 11/16 | 0.56 |
| D8N    | 1/2   | 7/8   | 0.69 |
| D10N   | 5/8   | 1     | 0.69 |
| D12N   | 3/4   | 1-1/8 | 0.69 |
| D14N   | 7/8   | 1-1/4 | 0.69 |
| D16N   | 1     | 1-1/2 | 0.81 |
| D20N   | 1-1/4 | 1-7/8 | 1.25 |
| D24N   | 1-1/2 | 2-1/4 | 1.50 |
| D32N   | 2     | 3     | 2.06 |

![](_page_47_Figure_3.jpeg)

Back Ferrule

|        | Т     |
|--------|-------|
| Duolok | Tube  |
| Part # | 0.D.  |
| D1BF   | 1/16  |
| D2BF   | 1/8   |
| D3BF   | 3/16  |
| D4BF   | 1/4   |
| D5BF   | 5/16  |
| D6BF   | 3/8   |
| D8BF   | 1/2   |
| D10BF  | 5/8   |
| D12BF  | 3/4   |
| D14BF  | 7/8   |
| D16BF  | 1     |
| D20BF  | 1-1/4 |
| D24BF  | 1-1/2 |
| D32BF  | 2     |

![](_page_47_Figure_6.jpeg)

### **Front Ferrule**

|        | Т     |
|--------|-------|
| Duolok | Tube  |
| Part # | O.D.  |
| D1FF   | 1/16  |
| D2FF   | 1/8   |
| D3FF   | 3/16  |
| D4FF   | 1/4   |
| D5FF   | 5/16  |
| D6FF   | 3/8   |
| D8FF   | 1/2   |
| D10FF  | 5/8   |
| D12FF  | 3/4   |
| D14FF  | 7/8   |
| D16FF  | 1     |
| D20FF  | 1-1/4 |
| D24FF  | 1-1/2 |
| D32FF  | 2     |

![](_page_47_Figure_9.jpeg)

### Ferrule Set

|        | Т    |
|--------|------|
| Duolok | Tube |
| Part # | O.D. |
| D1FS   | 1/16 |
| D2FS   | 1/8  |
| D3FS   | 3/16 |
| D4FS   | 1/4  |
| D5FS   | 5/16 |
| D6FS   | 3/8  |
| D8FS   | 1/2  |

A Ferrule Set (FS) consists of one front ferrule and one back ferrule and is conveniently packaged and sold in multiples of ten sets per "holding tube" housing. To order twenty (20) sets of the 1/4" 316 Stainless Steel front and back ferrules, specify: 20 pcs. ISSD4FS

Finger-tight assembly dimensions (shown in inches) are for reference only and subject to change.

## Components

![](_page_48_Picture_1.jpeg)

### **Knurled Nut**

|        | Т    |       |      |
|--------|------|-------|------|
| Duolok | Tube |       |      |
| Part # | O.D. | G     | L    |
| D1KN   | 1/16 | 5/16  | 0.31 |
| D2KN   | 1/8  | 7/16  | 0.47 |
| D3KN   | 3/16 | 1/2   | 0.47 |
| D4KN   | 1/4  | 9/16  | 0.50 |
| D5KN   | 5/16 | 5/8   | 0.53 |
| D6KN   | 3/8  | 11/16 | 0.56 |
| D8KN   | 1/2  | 7/8   | 0.69 |
| D10KN  | 5/8  | 1     | 0.69 |
| D12KN  | 3/4  | 1-1/8 | 0.69 |
| D14KN  | 7/8  | 1-1/4 | 0.69 |
| D16KN  | 1    | 1-1/2 | 0.81 |

![](_page_48_Figure_4.jpeg)

The knurled nut is designed for use with fittings used in applications where it has been determined by the user that a finger tight assembly procedure is acceptable. Typical applications include low pressure laboratory use of plastic tubing.

![](_page_48_Picture_6.jpeg)

### **Bulkhead Locknut**

|        | Т    |      |        |
|--------|------|------|--------|
| Duolok | Tube |      |        |
| Part # | O.D. | Α    | Н      |
| D1BN   | 1/16 | 0.13 | 5/16   |
| D2BN   | 1/8  | 0.22 | 1/2    |
| D3BN   | 3/16 | 0.22 | 9/16   |
| D4BN   | 1/4  | 0.22 | 5/8    |
| D5BN   | 5/16 | 0.28 | 11/16  |
| D6BN   | 3/8  | 0.27 | 3/4    |
| D8BN   | 1/2  | 0.31 | 15/16  |
| D10BN  | 5/8  | 0.36 | 1-1/16 |
| D12BN  | 3/4  | 0.41 | 1-3/16 |
| D14BN  | 7/8  | 0.41 | 1-3/8  |
| D16BN  | 1    | 0.41 | 1-5/8  |

![](_page_48_Figure_9.jpeg)

![](_page_48_Picture_10.jpeg)

**Tube Insert** 

| 1 0110 0 1       |              |              |                      |
|------------------|--------------|--------------|----------------------|
| Duolok<br>Part # | Tube<br>O.D. | Tube<br>I.D. | E<br>I.D.<br>of Bore |
| D3TI2            | 3/16         | 1/8          | 0.09                 |
| D4TI2            | 1/4          | 1/8          | 0.09                 |
| D4TI170          | 1/4          | 0.170        | 0.11                 |
| D4TI3            | 1/4          | 3/16         | 0.14                 |
| D5TI2            | 5/16         | 1/8          | 0.09                 |
| D5TI3            | 5/16         | 3/16         | 0.12                 |
| D5TI4            | 5/16         | 1/4          | 0.19                 |
| D6TI3            | 3/8          | 3/16         | 0.12                 |
| D6TI4            | 3/8          | 1/4          | 0.19                 |
| D8TI4            | 1/2          | 1/4          | 0.19                 |
| D8TI6            | 1/2          | 3/8          | 0.31                 |
| D10TI6           | 5/8          | 3/8          | 0.31                 |
| D10TI8           | 5/8          | 1/2          | 0.44                 |
| D12TI8           | 3/4          | 1/2          | 0.44                 |
| D12TI10          | 3/4          | 5/8          | 0.56                 |
| D16TI12          | 1            | 3/4          | 0.69                 |
|                  |              |              |                      |

Soft, pliable tubing

Tube Insert

![](_page_48_Figure_15.jpeg)

Duolok

**Tube Fitting** 

In general, Duolok tube fittings may be used with a variety of plastic tube materials without any special preparations. However, very soft-wall, pliable tubing such as Tygon<sup>®</sup> needs a tube insert for support prior to insertion in the Duolok tube fitting. The standard Duolok tube fitting installation instructions (see page 9) are then followed for proper make-up.

![](_page_48_Figure_17.jpeg)

![](_page_48_Figure_18.jpeg)

SSP flareless instrumentation quality tube fittings have been designed and manufactured to provide reliable leak free connections in a wide variety of applications. The design characteristics of the tube fittings compensate for many of the field variables involved in the installation of the tube fittings and with the tolerances, wall thickness, finish and quality of the tubing. A reliable leak free tubing system will be achieved by combining the proper selection and handling of tubing with the proper tube fitting selection and installation. The following information is provided to assist in the tube selection process.

### MATERIAL

The tubing material chosen must be compatible with the system's contained media, pressure and temperature, as well as with the environment in which it will be installed. Also, the tubing and tube fitting materials should be similar for optimum sealing action to occur (stainless fittings for stainless tube, brass fittings for copper tube, carbon steel fittings for carbon steel tube, etc.). The mixing and contact of dissimilar materials may leave the system susceptible to galvanic corrosion and/or not allow proper tube fittings have been designed and manufactured to function within the hardness ranges allowed for similar tubing materials by applicable ASTM specifications as referred to in Tables 1-4.

### PRESSURE AND FLOW

The size of the tube's outside diameter (O.D.) and the necessary wall thickness are determined by the system's pressure and flow requirements. Tables 1-4 detail the suggested tubing sizes and wall thick-nesses for use with instrumentation tube fittings. Additionally, the tables provide the maximum allowable working pressures for each size of tube recommended for use with instrumentation tube fittings. If no pressure is shown on the table for a particular size, the tube is not recommended for use with instrumentation tube fittings. The tubing system should not be utilized above the tube's maximum allowable working pressure; however, instrumenta-tion tube fittings have been tested as leak tight to the burst pressure of the tubing in all recommended sizes and wall thicknesses.

### TEMPERATURE

The system's operating temperature may affect the initial choice of tubing material and may also affect the maximum allowable working pressure for the given tube size (see Table 5 for temperature stress factors).

### LIGHT GAS SERVICE

Light gases such as hydrogen, helium, nitrogen, etc. have extremely small molecules which can be released through the smallest of leak paths including tubing surface imperfections or defects. To provide a successful connection for light gas service, the tubing must have a thick enough wall to provide resistance for the setup action of the ferrules to further compensate for the tube's potential surface condition. Tables 1-4 show the tubing sizes and wall thicknesses recommended for light gas service.

### HANDLING AND INSTALLATION

Surface scratches and gouges on tubing are a source of potential leaks. Some precaution when handling the tubing can help reduce surface scratches and maintain the surface finish as originally intended by the manufacturer. Tubing should never be dragged across rocks, blacktop, pavement, or the tubing storage rack as scratches and gouges can occur. Sharp blades should always be used in the tube cutters or hacksaws used to cut the tubing so as to provide a clean, square cut. Dull cutting blades can cause internal and external hanging burrs, and cause the tubing to become oval and affect proper insertion within the fitting. As a good handling practice, tubing should always be deburred prior to tube fitting installation to help assure easy and complete tube insertion. Additionally, for bent tube assemblies, it is important to bend tubing prior to installing tube fittings, and to provide a sufficient straight length of tubing after the bend to allow the tube to be fully inserted into the fitting. See Figure A and Table 7 on page 53 for additional information. Also, to eliminate weight stress from the tubing upon the fitting and to provide additional system support for vibration and thermal shock resistance, the tubing should always be supported by tube hangers, clamps or trays.

## Selection Guide for Instrumentation Fittings & Tubing

|             | STAINLESS STEEL TUBING - TABLE 1<br>Maximum Allowable Working Pressure (PSIG) |                                 |      |      |       |      |       |       |       |      |      |      |        |           |           |        |
|-------------|---|---------------------------------|------|------|-------|------|-------|-------|-------|------|------|------|--------|-----------|-----------|--------|
| Tube O.D.   |   | Wall Thickness of Tube (Inches) |      |      |       |      |       |       |       |      |      |      |        |           |           |        |
| (Size (in.) | .010  | .012                            | .014 | .016 | .020  | .028 | .035  | .049  | .065  | .083 | .095 | .109 | .120   | .134      | .156      | .188   |
| 1/16        | 5600  | 6850                            | 8150 | 9500 | 12100 |      |       |       |       |      |      |      |        |           |           |        |
| 1/8         |   |                                 |      |      |       | 8550 | 11000 |       |       |      |      |      | Note:  | For ligh  | t gas sei | rvice, |
| 3/16        |   |                                 |      |      |       | 5450 | 7000  | 10300 |       |      |      |      | use tu | ibing wit | h wall    |        |
| 1/4         |   |                                 |      |      |       | 4000 | 5100  | 7500  | 10300 |      |      |      | thickn | ess outs  | side of   |        |
| 5/16        |   |                                 |      |      |       |      | 4050  | 5850  | 8050  |      |      |      | scree  | ned area  | Э.        |        |
| 3/8         |   |                                 |      |      |       |      | 3300  | 4800  | 6550  |      |      |      |        |           |           |        |
| 1/2         |   |                                 |      |      |       |      | 2450  | 3500  | 4750  | 6250 |      |      |        |           |           |        |
| 5/8         |   |                                 |      |      |       |      |       | 2950  | 4000  | 5200 | 6050 |      |        |           |           |        |
| 3/4         |   |                                 |      |      |       |      |       | 2400  | 3300  | 4250 | 4950 | 5800 |        |           |           |        |
| 7/8         |   |                                 |      |      |       |      |       | 2050  | 2800  | 3600 | 4200 | 4850 |        |           |           |        |
| 1           |   |                                 |      |      |       |      |       |       | 2400  | 3150 | 3650 | 4200 | 4700   |           |           |        |
| 1-1/4       |   |                                 |      |      |       |      |       |       |       | 2450 | 2850 | 3300 | 3650   | 4150      | 4900      |        |
| 1-1/2       |   |                                 |      |      |       |      |       |       |       |      | 2350 | 2700 | 3000   | 3400      | 4000      | 4900   |
| 2           |   |                                 |      |      |       |      |       |       |       |      |      | 2000 | 2200   | 2500      | 2900      | 3600   |

**Calculation Basis:** Annealed, seamless 304 or 316 stainless steel tubing ASTM A-269 or equivalent. System temperatures between -20°F and 100°F with allowable stress of 20,000 psi. Ultimate tensile strength of 75,000 psi. Safety factor of 4.

**Reference:** ANSI B 31.3 Code. (For more specific working pressure information regarding a particular tubing, consult with the actual manufacturer of the tubing.)

**Note:** For welded and drawn tubing, a derating factor must be utilized. For double welded tube, multiply the above pressure rating by .85; and for single welded tube by .80 (ANSI B 31, Table A-1B).

**Suggested Tube Ordering Information:** Specify the outside diameter and wall thickness of annealed, seamless or welded and drawn 316 or 304 stainless steel tubing of ASTM A-269, A-249, A-213 or equivalent. Also specify high quality tubing to be free of scratches, and suited for bending with material hardness not to exceed Rb 90.

| I          | COPPER TUBING - TABLE 2<br>Maximum Allowable Working Pressure (PSIG) |                                 |      |      |                |           |         |       |  |  |  |
|------------|--|---------------------------------|------|------|----------------|-----------|---------|-------|--|--|--|
| Tube O.D.  |  | Wall Thickness of Tube (Inches) |      |      |                |           |         |       |  |  |  |
| Size (in.) | .028   | .035                            | .049 | .065 | .083           | .095      | .109    | .120  |  |  |  |
| 1/8        | 2700   | 3600                            |      |      |                |           |         |       |  |  |  |
| 3/16       | 1700   | 2225                            | 3450 |      | Note:          | For light | gas ser | vice, |  |  |  |
| 1/4        | 1250   | 1600                            | 2475 | 3475 | use tul        | oing with | wall    |       |  |  |  |
| 5/16       |  | 1250                            | 1900 | 2675 | thickne        | ess outs  | ide of  |       |  |  |  |
| 3/8        |  | 1050                            | 1550 | 2150 | screen         | ied area  | -       |       |  |  |  |
| 1/2        |  | 750                             | 1150 | 1550 | 2050           |           |         |       |  |  |  |
| 5/8        |  |                                 | 900  | 1200 | 1600           | 1850      |         |       |  |  |  |
| 3/4        |  |                                 | 700  | 1000 | 1275 1500 1775 |           |         |       |  |  |  |
| 7/8        |  |                                 | 600  | 850  | 1075 1250 1500 |           |         |       |  |  |  |
| 1          |  |                                 | 550  | 700  | 950            | 1100      | 1300    | 1400  |  |  |  |

**Calculation Basis:** Annealed (Temper 060), seamless copper tubing ASTM B-75 or equivalent. System temperatures between -20°F and 100°F with allowable stress of 6000 psi. Ultimate tensile strength of 30,000 psi. Safety factor of 5.

**Reference:** ANSI B 31.3 Code. (For more specific working pressure information regarding a particular tubing, consult with the actual manufacturer of the tubing.)

**Suggested Tube Ordering Information:** Specify the outside diameter and wall thickness of annealed (Temper 060), seamless copper tubing of ASTM B-75, B-68, or equivalent specification. Also specify high quality tubing to be free of scratches, and suited for bending.

Additionally Acceptable: Annealed (Temper O) copper water tubing, Type K or Type L (ASTM B-88). No embossed markings allowed.

## Selection Guide for Instrumentation Fittings & Tubing

|            | CARBON STEEL TUBING - TABLE 3<br>Maximum Allowable Working Pressure (PSIG) |                                 |      |      |      |      |      |      |      |   |           |         |       |
|------------|--|---------------------------------|------|------|------|------|------|------|------|---|-----------|---------|-------|
| Tube O.D.  |  | Wall Thickness of Tube (Inches) |      |      |      |      |      |      |      |   |           |         |       |
| Size (in.) | .028   | .035                            | .049 | .065 | .083 | .095 | .109 | .120 | .134 | .148                                      | .165      | .180    | .220  |
| 1/8        | 8100   | 10500                           |      |      |      |      |      |      |      |   |           |         |       |
| 3/16       | 5150   | 6700                            | 9900 |      |      |      |      |      |      | Note:                                     | For light | gas ser | vice, |
| 1/4        | 3750   | 4850                            | 7100 | 9900 |      |      |      |      |      | use tubing with wall thickness outside of |           |         |       |
| 5/16       |  | 3800                            | 5500 | 7600 |      |      |      |      |      |   |           |         |       |
| 3/8        |  | 3100                            | 4500 | 6200 |      |      |      |      |      | screen                                    | ed area.  |         |       |
| 1/2        |  | 2300                            | 3300 | 4500 | 5950 |      |      |      |      |   |           |         |       |
| 5/8        |  | 1800                            | 2600 | 3500 | 4600 | 5350 |      |      |      |   |           |         |       |
| 3/4        |  |                                 | 2150 | 2900 | 3750 | 4375 | 5100 |      |      |   |           |         |       |
| 7/8        |  |                                 | 1800 | 2450 | 3200 | 3700 | 4300 |      |      |   |           |         |       |
| 1          |  |                                 | 1550 | 2100 | 2750 | 3200 | 3700 | 4125 |      |   |           |         |       |
| 1-1/4      |  |                                 |      | 1650 | 2150 | 2500 | 2900 | 3200 | 3600 | 4050                                      | 4600      | 5000    |       |
| 1-1/2      |  |                                 |      |      | 1800 | 2000 | 2400 | 2600 | 3000 | 3300                                      | 3700      | 4100    | 5100  |
| 2          |  |                                 |      |      |      | 1500 | 1700 | 1900 | 2200 | 2400                                      | 2700      | 3000    | 3700  |

**Calculation Basis:** Annealed, seamless carbon steel tubing ASTM A-179 or equivalent. System temperatures between -20°F and +100°F with allowable stress of 15,700 psi. Ultimate tensile strength of 47,500 psi. Safety factor of 4.

**Reference:** ANSI B 31.3 Code. (For more specific working pressure information regarding a particular tubing, consult with the actual manufacturer of the tubing.)

**Suggested Tube Ordering Information:** Specify the outside diameter and wall thickness of annealed, seamless carbon steel tubing of ASTM A-179 or equivalent specification. Also specify high quality tubing to be free of scratches, and suited for bending with material hardness not to exceed Rb 72.

| 1          | MONEL <sup>®</sup> ALLOY 400 TUBING - TABLE 4<br>Maximum Allowable Working Pressure (PSIG) |       |      |      |           |           |          |           |  |  |
|------------|--|-------|------|------|-----------|-----------|----------|-----------|--|--|
| Tube O.D.  | Tube O.D. Wall Thickness of Tube (Inches)  |       |      |      |           |           |          |           |  |  |
| Size (in.) | .028   | .035  | .049 | .065 | .083      | .095      | .109     | .120      |  |  |
| 1/8        | 8000   | 10450 |      |      |           |           |          |           |  |  |
| 1/4        | 3750   | 4800  | 7000 | 9800 | Note: F   | or light  | gas serv | rice, use |  |  |
| 3/8        |  | 3100  | 4450 | 6150 | tubing v  | with wall | thicknes | ss        |  |  |
| 1/2        |  | 2300  | 3300 | 4450 | outside   | ofscree   | ened are | a.        |  |  |
| 3/4        |  |       | 2250 | 3050 | 4000 4600 |           |          |           |  |  |
| 1          |  |       |      | 2250 | 2900      | 3400      | 3900     | 4350      |  |  |

**Calculation Basis:** Annealed, seamless Monel Alloy 400 tubing ASTM B-165 or equivalent. System temperatures between -20°F and 100°F with allowable stress of 18,700 psi. Ultimate tensile strength of 70,000 psi. Safety factor of 4. Table values are per the ANSI/ASME B 31.3 Code for temperatures from -325°F to only +100°F. Monel derates fast at elevated temperatures. (For more specific working pressure information regarding a particular tubing, consult with the actual manufacturer of the tubing.)

**Suggested Tube Ordering Information:** Specify the outside diameter and wall thickness of annealed, seamless Monel Alloy 400 tubing of ASTM B-165 or equivalent specification. Also specify high quality tubing to be free of scratches, and suited for bending with material hardness not to exceed Rb 75.

## Selection Guide for Instrumentation Fittings & Tubing

| STRESS FACTORS FOR DETERMINING TUBING PRESSURE<br>RATINGS AT ELEVATED TEMPERATURES - TABLE 5 |         |         |          |        |        |        |  |  |  |  |  |  |
|--|---------|---------|----------|--------|--------|--------|--|--|--|--|--|--|
| TEMPERATURE STRESS FACTORS   |         |         |          |        |        |        |  |  |  |  |  |  |
| Temp   | erature | Stainle | ss Steel | Carbon |        | Monel® |  |  |  |  |  |  |
| °F   | °C      | 304SS   | 316SS    | Stee   | Copper | 400    |  |  |  |  |  |  |
| 100  | 38      | 1.00    | 1.00     | 1.00   | 1.00   | 1.00   |  |  |  |  |  |  |
| 200  | 93      | 1.00    | 1.00     | .96    | .80    | .88    |  |  |  |  |  |  |
| 300  | 149     | 1.00    | 1.00     | .90    | .78    | .82    |  |  |  |  |  |  |
| 400  | 204     | .94     | .97      | .86    | .50    | .79    |  |  |  |  |  |  |
| 500  | 260     | .88     | .90      | .82    | n/a    | .79    |  |  |  |  |  |  |
| 600  | 316     | .82     | .85      | .77    | n/a    | .79    |  |  |  |  |  |  |
| 700  | 371     | .80     | .82      | .73    | n/a    | .79    |  |  |  |  |  |  |
| 800  | 427     | .76*    | .80*     | .59    | n/a    | .76    |  |  |  |  |  |  |
| 900  | 482     | .73*    | .78*     | .41    | n/a    | .43    |  |  |  |  |  |  |
| 1000   | 538     | .69*    | .73*     | .16    | n/a    | n/a    |  |  |  |  |  |  |
| 1200   | 649     | .30*    | .37*     | n/a    | n/a    | n/a    |  |  |  |  |  |  |

\* The precipitation of chromium carbides potentially resulting in intergranular corrosion may occur when exposed to operating temperatures above 800°F. Consult the factory for further information.

**Instructions:** To determine maximum allowable working pressures for tubing at elevated temperatures, multiply the applicable tube's maximum allowable working pressure from Table 1-4 by the corresponding temperature stress factor from Table 5.

| SSP NPT PIPE END PRESSURE RATINGS, ANSI/ASME B 31.3 - TABLE 6 |        |           |        |  |     |      |     |        |     |              |     |      |      |  |  |
|---|--------|-----------|--------|--|-----|------|-----|--------|-----|--------------|-----|------|------|--|--|
| 316 STAINL  |        |           |        | ESS STE  | EL  |      | BR  | ASS    |     | CARBON STEEL |     |      |      |  |  |
| NPT/ISO   |        | Male      |        | Female   |     | Male |     | Female |     | Male         |     | Fen  | nale |  |  |
| Pipe Size   | Size   | psig      | bar    | psig   | bar | psig | bar | psig   | bar | psig         | bar | psig | bar  |  |  |
| 1/16"   | 1      | 11050     | 760    | 6750   | 460 | 5550 | 380 | 3350   | 230 | 11050        | 760 | 6750 | 460  |  |  |
| 1/8"  | 2      | 10050     | 690    | 6550   | 450 | 5050 | 350 | 3250   | 220 | 10050        | 690 | 6550 | 450  |  |  |
| 1/4"  | 4      | 8050      | 550    | 6650   | 460 | 4050 | 280 | 3350   | 230 | 8050         | 550 | 6650 | 460  |  |  |
| 3/8"  | 6      | 7850      | 540    | 5350   | 370 | 3950 | 270 | 2650   | 180 | 7850         | 540 | 5350 | 370  |  |  |
| 1/2"  | 8      | 7750      | 530    | 4950   | 340 | 3850 | 260 | 2450   | 170 | 7750         | 530 | 4950 | 340  |  |  |
| 3/4"  | 12     | 7350      | 510    | 4650   | 320 | 3650 | 250 | 2350   | 160 | 7350         | 510 | 4650 | 320  |  |  |
| 1"  | 16     | 5350      | 370    | 4450   | 310 | 2650 | 180 | 2250   | 150 | 5350         | 370 | 4450 | 310  |  |  |
| 1-1/4"  | 20     | 6000      | 410    | 5000   | 350 | 3000 | 200 | 2500   | 170 | 6000         | 410 | 5000 | 350  |  |  |
| 1-1/2"  | 24     | 5000      | 340    | 4600   | 310 | 2500 | 170 | 2300   | 150 | 5000         | 340 | 4600 | 310  |  |  |
| 2"  | 32     | 3900      | 270    | 3900   | 270 | 1900 | 300 | 1900   | 130 | 3900         | 270 | 3900 | 270  |  |  |
| Reference   | e: bar | = .0690 > | ( psig | To obtain ANSI/ASME B 31.1 values, multiply ANSI/ASME B 31.3 values by .94 |     |      |     |        |     |              |     |      |      |  |  |

![](_page_52_Figure_5.jpeg)

### INSTALLING TUBE FITTINGS NEAR TUBE BENDS

When installing fittings near tube bends, it is important to **bend tubing prior to installing tube fittings** and there must be a sufficient straight length (SL) of tubing to allow the tube to be bottomed in the fitting. Note Table 7 for details.

#### TABLE 7

|   |  | owed for specified wall  |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |
|---|--|--|------|------|------|-------|-------|-------|--------|-------|-------|--------|--------|--------|---------|-------|--|--|
| thickness and tube size as<br>recommended by tubing | thickness and tube size as   | T = Tube   | 1/10 | 1/0  | 2/46 | 1/4   | E/4 C | 2/0   | 1/0    | E /0  | 2/4   | 7/0    | 4      | 4 4 /4 | 1 1/0   | 2     |  |  |
|   | O.D.(in.)  | 1/10   | 1/0  | 3/10 | 1/4  | 0/10  | 3/0   | 1/2   | 0/6    | 3/4   | 1/0   | 1      | 1-1/4  | 1-1/2  | 2       |       |  |  |
|   | · manufacturer.  | *SL=Minimum  |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |
| SL Min<br>Ienę<br>tube                              | Minimum straight tube<br>length required from end of<br>tube to beginning of bend. | Straight   | 1/2  | 3/4  | 3/4  | 13/16 | 7/8   | 15/16 | 1-3/16 | 1-1/4 | 1-1/4 | 1-5/16 | 1-9/16 | 2      | 2-13/32 | 3-1/4 |  |  |
|   |  | Length of  |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |
|   |  | Tube (in.)   |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |
| т   | Tube outside diameter.   | R Radius of tube bend as recommended by bender manufacturer                |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |
|   |  | * Consult the factory on an application by application basis for variance. |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |
|   |  |  |      |      |      |       |       |       |        |       |       |        |        |        |         |       |  |  |

![](_page_52_Picture_10.jpeg)

IMPROPER SELECTION OR IMPROPER USE OF THE PRODUCTS DESCRIBED HEREIN OR RELATED ITEMS CAN CAUSE PERSONAL INJURY AND PROPERTY DAMAGE.

It is the sole responsibility of the system designers and users to properly select and use products for their specific applications. This document has been printed for users with technical expertise as a reference for further investigation to determine specific product needs relative to design requirements.

## **Safety Information / Warranty**

### Safety

To help ensure the safe and reliable performance of tube fitting products, complete system design must be considered prior to the installation of the tubing and tube fittings. Determining the design compatibility of materials, media, flows, temperatures and pressures; as well as implementing proper installation, operation and maintenance of the system are the responsibilities of the systems' owners, designers and users.

### **SSP Safety Reminders**

All SSP products are designed and manufactured with safety in mind. The following is a limited list of general safety tips as reminders of good safety practices:

- Do not install, tighten or loosen a tube fitting while the system is under pressure.
- Do not loosen a tube fitting, nut or plug to relieve or bleed system pressure.
- Always use a back-up wrench to hold the tube fitting body steady when tightening or loosening tube fitting nuts.
- There is no need to disassemble a new tube fitting prior to use.
- Use proper thread lubricants and sealants on tapered pipe threads.

- Very soft, pliable plastic tubing requires a tube insert.
- Tube fitting and tubing material should be similar (stainless steel fittings on stainless steel tubing, brass fittings on copper tubing, etc.) with the tubing material being fully annealed. For more specific information, refer to the Selection Guide for Instrumentation Fittings and Tubing on pages 50 - 53.
- Do not weld tube fittings that are assembled. Prior to welding, remove the nut and ferrules and protect the seat and thread area of the tube fitting by covering with a plug or another nut. (See page 30 for more information.)

### **Duolok**<sup>®</sup> Tube Fittings

### **LIFETIME LIMITED WARRANTY**

SSP guarantees all Duolok tube fittings and Duolok tube fitting components to be free from defects in materials and workmanship. Additionally, SSP guarantees Duolok product performance to the published catalog specifications when properly installed according to the catalog selection and installation instructions. To initiate a warranty claim, suspected defective product must be returned to SSP with the nature of potential defect documented for factory evaluation. Any product with a determined defect in material or workmanship will be replaced with equivalent product at no charge.

This warranty comprises the sole and entire warranty pertaining to items provided hereunder. There is no other warranty, guarantee, express or implied representation of any kind whatsoever. All other warranties including, but not limited to, merchantability and fitness for purpose, whether express, implied, or arising by operation of law, course of dealing, or trade usage are hereby disclaimed. There are no warranties which extend beyond the description on the face hereof; and this warranty does not apply in cases of abuse, mishandling, or normal use depreciation. In no event, whether alleged to arise from breach of contract, express or implied warranty, by operation of law, negligence or otherwise, will SSP be liable for any incidental, consequential, lost property, or other special damages of any kind whatsoever. The exclusive, only remedy under this warranty is the replacement of determined defective parts as set forth above.

In addition to Duolok Tube Fittings, SSP Instrumentation also offers Unilok and Griplok Instrumentation Tube Fittings; TruFit Pipe, Weld, Hose and Adapter Fittings; and FloLok Valves. Contact your SSP Instrumentation Distributor for more information.

![](_page_54_Picture_2.jpeg)

![](_page_54_Picture_3.jpeg)

**Griplok**<sup>®</sup> Tube Fittings

![](_page_54_Picture_5.jpeg)

VALVES FOR INSTRUMENTATION & PROCESS SYSTEMS

FloLok

Valves

FloLok<sup>®</sup> Valves

# Duolok<sup>a</sup> Tube Fittings

AUTHORIZED DISTRIBUTOR

![](_page_55_Picture_2.jpeg)

8250 Boyle Parkway Twinsburg, Ohio 44087-2200 Telephone: (330) 425-4250 Fax: (330) 425-8116 www.mySSP.com

![](_page_55_Picture_4.jpeg)

Made in the USA

![](_page_55_Picture_6.jpeg)

SSP Instrumentation ILDPC-25B